


NASA CR-122478



(NASA-CR-122478) TASK 2: FLIGHT PROTOTYPE  
SYSTEM DESIGN REPORT, PULSED PLASMA SOLID  
PROPELLANT MICROTHRUSTER FOR THE W.J.  
Guman (Fairchild Industries, Inc.) Apr.  
1972 157 p

N72-31782

Unclas  
41138

CSCL 21C G3/28



**FAIRCHILD**  
REPUBLIC DIVISION



Reproduced by  
NATIONAL TECHNICAL  
INFORMATION SERVICE  
US Department of Commerce  
Springfield, VA 22151

156 PB

FRD 4082

TASK 2 - FLIGHT PROTOTYPE SYSTEM  
DESIGN REPORT

Pulsed Plasma Solid Propellant Microthruster  
for the Synchronous Meteorological Satellite

Interim Report for Period  
November 1971-April 1972

**FAIRCHILD**

Fairchild Republic Division Farmingdale, New York 11735

Details of illustrations in  
this document may be better  
studied on microfiche

FRD 4082

**TASK 2 - FLIGHT PROTOTYPE SYSTEM DESIGN REPORT**

**Pulsed Plasma Solid Propellant Microthruster for the Synchronous  
Meteorological Satellite**

Edited by        William J. Guman  
                  Fairchild Industries  
                  Fairchild Republic Division  
                  Farmingdale, L.I., New York 11735

**April 1972**

**Interim Report for Period November 1971 - April 1972**

**Prepared for**

**GODDARD SPACE FLIGHT CENTER  
Greenbelt, Maryland 20771**

6

**TECHNICAL REPORT STANDARD TITLE PAGE**

1. Report No.		2. Government Accession No.		3. Recipient's Catalog No.	
4. Title and Subtitle Task 2 - Flight Prototype System Design Report, Pulsed Plasma Solid Propellant Microthruster for the Synchronous Meteorological Satellite				5. Report Date April 1972	
				6. Performing Organization Code FRD 4082	
7. Author(s) Edited by W. J. Guman				8. Performing Organization Report No.	
9. Performing Organization Name and Address Fairchild Industries Fairchild Republic Division Farmingdale, New York 11735				10. Work Unit No.	
				11. Contract or Grant No. NAS 5-11494	
12. Sponsoring Agency Name and Address Goddard Space Flight Center Greenbelt, Maryland 20771 Mr. T. E. Williams				13. Type of Report and Period Covered Interim Task Report Nov. 1971-April 1972	
				14. Sponsoring Agency Code	
15. Supplementary Notes					
16. Abstract This report presents design details of the solid propellant pulsed plasma microthruster which was analyzed during the Task I effort. The design details presented shows that the inherent functional simplicity underlying the flight proven LES-6 design can be maintained in the SMS system design even with minimum weight constraints imposed. A 1293 hour uninterrupted vacuum test with the engineering thermal model simulating an 18.8 to 33 g environment of the propellant, its feed system and electrode assembly revealed that program thruster performance requirements could be met. This latter g environment is a more severe environment than will be ever encountered in the SMS spacecraft.					
17. Key Words (Selected by Author(s)) Electric Propulsion Pulsed Plasma Thruster Satellite Control Plasma Propulsion				18. Distribution Statement	
19. Security Classif. (of this report) Unclassified		20. Security Classif. (of this page) Unclassified		21. No. of Pages	
				22. Price*	

\*For sale by the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

## PREFACE

This report presents the results performed during Task 2 of the program. It presents the design and efforts supporting the design of the flight prototype solid propellant pulsed plasma propulsion system. The period of performance covered is from November 1971 to April 1972. The design effort contributions during this period of performance were primarily provided by the joint efforts of Messrs. G. Schweitzer and Mr. Katchmar at Fairchild Industries. The design efforts of the Power Conditioner were under the direction of Dr. E. T. Moore of Wilmore Electronics, Inc. The entire program was under the direction of Dr. W. J. Guman.

The results presented herein have shown that inherent functional simplicity underlying the flight proven LES-6 design can be maintained in the SMS system design even with minimum weight constraints imposed. Furthermore, a 1293 hour uninterrupted test with the engineering thermal model simulating an 18.8 to 33 g environment of the propellant, its feed system and electrode assembly revealed that program thruster performance requirements could be met. This latter g environment is a more severe environment than will be encountered on the spacecraft.

The material presented in this report primarily describes the system design by reference to corresponding tentative drawings provided.

## CONTENTS

<u>Section</u>		<u>Page</u>
1.0	INTRODUCTION . . . . .	1
1.1	Brief Description of Major Overall Subassembly . . . . .	1
2.0	THRUSTER SUBASSEMBLY DESIGN . . . . .	7
2.1	Thruster . . . . .	7
2.2	Propellant Subsystem . . . . .	11
2.3	Electrical Subsystem . . . . .	11
2.4	Structural Packaging . . . . .	15
2.4.1	Mechanical . . . . .	15
2.4.2	Electrical Isolation . . . . .	16
2.5	List of Thruster Drawings Presented . . . . .	16
3.0	POWER CONDITIONER DESIGN . . . . .	19
3.1	List of Power Conditioner Drawings Presented . . . . .	19
4.0	SUPPLEMENTARY SUPPORTING STUDIES . . . . .	21
4.1	Simulated Hi-g Acceleration Thruster Operation . . . . .	21
4.2	Thruster Mounting Hole Location Change . . . . .	23
4.3	Further Structural Considerations of Vibration Environment . . . . .	27
4.3.1	Fore and Aft Motion of Capacitor . . . . .	28
4.3.2	Rear Main Thruster Mount . . . . .	29
4.3.3	Exhaust Cone . . . . .	30
4.4	Weight Considerations . . . . .	31
5.0	PROGRAM FOR NEXT REPORT PERIOD . . . . .	33
6.0	CONCLUSIONS . . . . .	33
7.0	REFERENCE MATERIAL . . . . .	33
7.1	References . . . . .	33
7.2	Appendices . . . . .	33
	Appendix A. List of Applicable Documents . . . . .	A-1
	Appendix B. Sample Specification . . . . .	B-1 thru B-23
	Appendix C. Tentative Drawings of Thruster Subassembly . . . . .	C-1 thru C-57
	Appendix D. Tentative Drawings of Wilmore Electronics Power Conditioner . . . . .	D-1 thru D-33

## ILLUSTRATIONS

<u>Figure</u>		<u>Page</u>
1	Major and Minor Assemblies . . . . .	2
2	Schematic of Propulsion System . . . . .	3
3	Engineering Model of Flight Prototype Thruster . . . . .	4
4	Capacitor Case - Faceplate Subassemblies . . . . .	8
5	Thruster Discharge Path Major Subassembly . . . . .	10
6	Propellant Subsystem Without Propellant . . . . .	12
7	Centerbeam Positioned in Thruster Subassembly . . . . .	13
8	Breadboard Thruster Electronics Positioned in Thruster Subassembly . . . . .	14
9	Housing Assembly . . . . .	C-1
10	Forward Mount, Aft Mount . . . . .	C-3
11	Bulkhead Assembly, Enclosure . . . . .	C-5
12	Capacitor Case Assembly, Case, Cover . . . . .	C-7
13	Collector Plate, Negative . . . . .	C-9
14	Standoffs, Thermal . . . . .	C-11
15	Insulators . . . . .	C-13
16	Electrode-Positive . . . . .	C-15
17	Collector Plate-Positive . . . . .	C-17
18	Mykroy Insulator . . . . .	C-19
19	Electrode Negative . . . . .	C-21
20	Insulator, Mykroy Sides . . . . .	C-23
21	Beam Assembly, Covers, End Closure . . . . .	C-25
22	Electrical Interface Cover . . . . .	C-27
23	Forward Faceplate Assembly . . . . .	C-29
24	Rear Faceplate Assembly . . . . .	C-31
25	Shield . . . . .	C-33
26	Bridge . . . . .	C-35
27	Transformer Base . . . . .	C-37
28	Delay Pulse Generator Board Assembly . . . . .	C-39
29	Delay Pulse Generator Drill Drawing . . . . .	C-41
30	Delay Pulse Generator Artwork . . . . .	C-43
31	Pulse Driver Assembly . . . . .	C-45

ILLUSTRATIONS (Cont'd)

<u>Figure</u>		<u>Page</u>
32	Pulse Driver Drill Drawing . . . . .	C-47
33	Pulse Driver Artwork . . . . .	C-49
34	Exhaust Cone Assembly . . . . .	C-51
35	Capaciter, SCD . . . . .	C-53
36	Igniter Plug, SCD . . . . .	C-55
37	Alignment Mirror . . . . .	C-57
38	Subassembly High Voltage Power Conditioner . . . . .	D-1
39	Subassembly Delay Trigger Generator . . . . .	D-3
40	Subassembly Auxiliary Power Supply . . . . .	D-5
41	Subassembly Comparator Regulator . . . . .	D-7
42	Subassembly Power Transformer . . . . .	D-9
43	Drill Drawing for 15C0181 . . . . .	D-11
44	Drill Drawing for 15C0182 . . . . .	D-13
45	Drill Drawing for 15C0185 . . . . .	D-15
46	Drill Drawing for 15C0188 . . . . .	D-17
47	Drill Drawing for 15C0189 . . . . .	D-19
48	Schematic for Subassembly 12C0051 . . . . .	D-21
49	Schematic for Subassembly 12C0052 . . . . .	D-23
50	Schematic for Subassembly 12C0050 . . . . .	D-25
51	Schematic for Subassembly 12C0053 . . . . .	D-27
52	Converter Schematic . . . . .	D-29
53	Enclosure . . . . .	D-31
54	Cover . . . . .	D-33
55	Simulated Hi-g Test on Thrust Balance . . . . .	21
56	Post Hi-g Test Frontal View . . . . .	24
57	Anode of Hi-g Test . . . . .	25
58	Cathode of Hi-g Test . . . . .	26
59	Idealized Spoke of Faceplate . . . . .	28
60	Cone Surface Configuration . . . . .	30



ILLUSTRATIONS (Cont'd)

<u>Table</u>		<u>Page</u>
1	Thruster Drawings Presented . . . . .	17
2	Power Conditioner Drawings Presented . . . . .	19
3	Simulated Hi-g Test (Log 136-4) . . . . .	22
4	Breakdown of Revised Thruster Weight . . . . .	32

## 1.0 INTRODUCTION

This Task 2 report presents details of the thruster and power conditioner design whose analysis was presented in Reference 1.

Since the major part of the Task 2 effort was concerned with the system design, this report will be primarily comprised of the tentative drawings of the components of the design that were produced during the Task 2 design effort. Besides the drawings, presented in Appendix C, a relatively large number of specifications were also written for in-process testing of subassemblies to be fabricated. Rather than presenting these latter specification documents in this report, they are presented by title in tabular form in Appendix A with one sample presented as Appendix B.

Some supplementary supporting studies were also performed in conjunction with the final design and the results of these latter studies are presented in Section 4 of this report. Sections 2 and 3 present details of the design of the thruster and power conditioner, respectively.

Because the propulsion system is comprised of many components, it is necessary to present a discussion of the system in some orderly manner. Figure 1 presents a breakdown of the propulsion system in terms of major assemblies and then subsequent subassemblies. The description of the design will be presented in a manner which follows the layout presented in Figure 1.

### 1.1 BRIEF DESCRIPTION OF MAJOR OVERALL SUBASSEMBLY

Figure 2 schematically presents the complete propulsion system. Figure 3 shows an engineering model of the thruster without the power conditioner. Relevant callouts are provided to locate major components and subassemblies. Fundamentally, the propulsion system is comprised of two major subassemblies:

- a) The thruster subassembly, and
- b) The converter-charger subassembly.




Figure 1. Propulsion System Assembly and Subassemblies




Figure 2. Schematic of Propulsion System




Figure 3. Engineering Model of Flight Prototype Thruster

The converter-charger subassembly is mechanically integrated to the thruster subassembly by bolting it: 1) to the PC145D1015 bulkhead, 2) to the PC145D1013-2 aft mount and by means of two fins on the converter-charger to 3) the PC145D1010 housing assembly. The aft mount cited also represents one of the three system interface mounts to the spacecraft. The aft mount is also bolted to the lower part of the PC145D1040 centerbeam. Electrical interfacing between the two major subassemblies is RFI shielded by the PC145D1043 cover.

The three propulsion system mechanical interfaces to the spacecraft are thus by means of one PC145D1013-2 aft mount cited above and the two PC145D1013-1 forward mounts. These latter forward mounts have been analyzed and redesigned to be located exterior to the thruster package (see drawing PC145D1013-1). The basis for the relocation of the forward mounts is presented in Section 4.2 of this report.

The major thruster subassembly is basically the solid propellant pulsed plasma thruster without the power supply (see Figure 3). The latter being provided by the converter-charger. Section 2 will present a description of design details of the thruster subassembly.

PRECEDING PAGE BLANK NOT FILMED

## 2.0 THRUSTER SUBASSEMBLY DESIGN

By reference to Figure 1, the thruster assembly is comprised of the 1) thruster, 2) propellant subsystem, 3) electrical subsystem, and 3) structural packaging, respectively. These will now be briefly described. Reference will be made to appropriate preliminary drawing numbers identifying parts described.

### 2.1 THRUSTER

The thruster is represented by the energy storage capacitor (PC145D1090), the provision incorporated to transfer the capacitively stored energy as efficiently as possible to the electrode nozzle, appropriate electrical insulation and the exhaust cone assembly (PC145D1080). Provisions made to transfer energy efficiently from the capacitors to the electrode nozzles is as follows: Each of the two energy storage capacitors is contained in a thin walled aluminum cylindrical case (PC145D1021). The rear of this case has removable covers (PC145D1022), whereas the front outer periphery of each case is electron beam welded to the negative collector plate (PC145D1023). This subassembly can be seen in the top of Figure 4. The negative terminal (i.e., stud) of each capacitor is passed through the hole of each rear cover (PC145D1022) and secured by a nut. The positive terminal (i.e., stud) of each capacitor passes through a 0.250 in. dia. hole (see lower assembly in Figure 4) in the positive collector plate (PC145D1033). This positive collector plate assembly (PC145D1030) is electrically insulated on both sides. The side facing the capacitor case assembly is covered by teflon sheet. The opposite side of the plate by Shell Epon 828 epoxy. The latter epoxy actually is located between the spokes of the fiberglass face plate (PC145D1050) which may be seen in the lower view of Figure 4. This latter face plate is also described in Section 2.4.

As can be seen from the top assembly in Figure 4, the negative collector plate (PC145D1023) has a square cutout to allow the teflon fuel bar (PC145D1045) to pass into the electrode nozzle. The negative electrode (PC145D1036) is bolted to the negative collector plate (PC145D1023) as can be seen in the top view of Figure 4. The positive electrode (PC145D1032) is bolted to the positive collector plate (PC145D1033) as seen in the lower view of Figure 4. The propellant rod extends forward to the fuel retaining shoulder machined in the positive electrode. Mykroy insulators (PC145D1037) are located to each side of the teflon rod and situated between the electrodes. These two




Figure 4. Capacitor Case - Faceplate Subassemblies



Mykroy pieces are also seen in the lower view of Figure 4. With exception of plasma accelerating surfaces, the positive and negative electrode are covered with Mykroy insulators (PC145D1034).

With exception of the electrode area exposed to the plasma of the electrical discharge and the point of contact between the positive terminal of the capacitor and the positive collector plate, the entire subassembly shown in the lower part of Figure 4 is electrically insulated. Assurance of the quality of insulation is had by subjecting this subassembly to the tests specified in Fairchild specification PC145S8019.


The two igniter plugs (PC145D1091) are press fitted into the cathode as may be seen in the top view of Figure 4.

The positive collector plate (PC145D1033) is epoxied to the recessed cutout on the backside of face plate (PC145D1050). The latter has fasteners inserted into it so that the face plate (and thus the positive collector plate) can be screwed to the five front bolt holes (see top assembly in Figure 4) in each capacitor case, thus securing the entire discharge path as another major subassembly. This latter major subassembly (less the energy storage capacitors and rear lids) is shown as Figure 5. The Mykroy insulators (PC145D1034) without the PC145D1037 insulator in each electrode are more clearly seen in this latter figure.

The exhaust cone assembly (PC145D1080) is attached by screws to fasteners located in the face plate. The exhaust cone (PC145D1081) is lined with Mykroy (PC145D1084) and epoxied with Shell Epon 828 to all interior surfaces facing the plasma. The exterior of the cone is partially insulated on the outside aluminum surfaces by Shell 828 epoxy.

The thruster as described above is a functionally operative thruster if teflon propellant is provided and electrical leads are connected to charge the capacitor and fire the igniter plugs.

The positive lead charging the capacitor is connected to a tab located on the lower part of the positive collector plate (see PC145D1033). This tab is visible in the lower assembly of Figure 4. It is located at the lowest part of the positive collector plate in the lower outline of the face plate (both Figures 4 and drawing PC145D1033 should be used together to locate this tab.)



## 2.2 PROPELLANT SUBSYSTEM

The propellant subassembly (see Figure 6 for subassembly without propellant bar) is comprised of a propellant supporting track (center beam PC145D1040) its upper covers (PC145D1041) and end closure (PC145D1042), and the teflon fuel bar (PC145D1045), the drum (PC145D1047) and Negator spring (PC145D1046). Since the aluminum center beam (PC145D1040) contacts the thruster housing at the bulkhead (PC145D1015), it is at spacecraft ground. It is, therefore, necessary to electrically insulate it from the thruster discharge path. This insulation is achieved by having the forward (nozzle end) part of the centerbeam supported by a fiberglass support assembly (PC145D1051, 1052) which can be seen as the left subassembly in Figure 6. This latter fiberglass assembly is screwed onto the back side of face plate PC145D1050.

The center beam (PC145D1040), i.e., propellant track, is fabricated of two pieces of aluminum and electron beam welded together. Provisions are incorporated to fasten it to the top of the structural housing (PC145D1010), the rear bulkhead (PC145D1015), and the fiberglass support assembly mentioned above (PC145D1051, 1052). It is thus a main structural center beam of the propulsion system.

With the thruster connected to the bulkhead, the center beam is positioned as shown in Figure 7. The end cover (PC145D1042) of the center beam is removable to facilitate reloading or removal of the teflon propellant rod.

The center upper cover (PC1041-2) in the center beam has provisions to allow the thruster electrical subsystem to be secured to it. The Negator spring (PC145D1046) is fastened by the two center screws in the rear of the negative electrode directly to it. The other end of the spring is located on an insulating teflon drum (PC145D1047). The latter is secured to a notched cutout in the rear of the fuel bar by screws. While the negator spring is at the same ground potential of the thruster discharge circuit, it is thus electrically isolated from the thruster housing, i.e., spacecraft ground.

## 2.3 ELECTRICAL SUBSYSTEM

The thruster electrical subsystem is a separate subassembly straddling the center beam. The location of this subsystem relative to the remaining assemblies described may be seen in Figure 8. (Figure 8 shows the engineering breadboard version of the final circuitry.) It is comprised of three boards: 1) The discharge




Figure 6. Propellant Subsystem Without Propellant






Figure 7. Centerbeam Positioned in Thruster Subassembly




Figure 8. Breadboard Thruster Electronics Positioned in Thruster Subassembly

initiation circuit (PC145D1060) which is the circuit to the left of the center beam in Figure 8; 2) The delay pulse generator (PC145D1071), and 3) The pulse driver (PC145D1075). The latter two are stacked on top of each other separated by spacers (PC145D1074) and are located to the right of the center beam in Figure 8. These three boards are mechanically integrated to each other by an aluminum bridge (PC145D1063) which can also be seen in Figure 8. Upon installation in the thruster, all of these boards are secured by screwing them onto angular clips (PC145D1062) which are also secured to the housing (PC145D1011). Besides being secured to these clips the boards are attached to the bulkhead (PC145D1015) and by the fastening bridge (PC145D1063) to the center upper cover (PC145D1041-2) of the center beam (PC145D1040). The boards are thus not only securely fastened, but they become structurally integrating members of the thruster assembly. The printed circuitry assembly of the delay pulse generator and of the pulse driver are shown by drawings PC145D1071 and PC145D1075, respectively. As mentioned, in the manner installed, the electrical subsystem mechanically assists in distributing mechanical loads in the thruster subsystem. All electrical leads from the power conditioner and the thruster subassembly are passed through the bulkhead without standoffs. The latter wires are covered by an aluminum cover (PC145D1043) thus assuring EMI integrity. Venting of the cavity takes place into the thruster assembly.

## 2.4 STRUCTURAL PACKAGING

### 2.4.1 Mechanical

The thruster (see Section 2.1) is fastened to the bulkhead (PC145D1015) which has studs PC145D1017 pressed into it as can be seen in Figure 7. Insulators (PC145D1026) are used to assure an electrically insulated mounting. The bulkhead has a peripheral flange machined onto it so that the housing assembly PC145D1010 can be screwed onto it after it is slipped over the thruster. The cutout in bulkhead (PC145D1015) is sealed with respect to RFI leakage by the assembled center beam (PC145D1040) and the end cover (PC145D1042). These latter items have raised lips incorporated to preclude a direct line of view through the seams in the cutout after assembly. As stated in Reference 1, the housing (PC145D1011) has beads impressed into it (see Figure 3) to stiffen it. Furthermore, two stiffening Z sections (PC145D1012) are fastened to the downstream face (nozzle side) of the housing. The alignment mirror (PC145D1093) is located just below the lower Z section. The forward mounts

(PC145D1013-1) are attached to the two front lower corners of the housing, as can be seen in Figure 3.

The fiberglass face plate (PC145D1050) discussed in Section 2.1 may be considered a structural member. It has insulated PEM nuts not only for fastening the thruster to it, but also insulated PEM nuts for the screws which are screwed into it from the outside front face of the housing. Thus the housing assembly PC145D1010 is also secured to the face plate besides being screwed to the center beam, bulkhead and by clips to the electrical subsystem.

#### 2.4.2 Electrical Isolation

The thruster is rigidly attached to the bulkhead so that the thruster is electrically insulated from the bulkhead yet facilitating thermal conduction. An insulated bushing assembly (PC145D1026) and Beryllium Oxide washers (PC145D1025) are used for this purpose. The attachment of the thruster to the bulkhead is shown in PC145D1014 and Figure 8. (The Beryllium Oxide washers were not available at the time the photograph was taken. Fiberglass washers instead of the Beryllium Oxide washers are used during the phase of the assembly shown in Figure 8.)

A cover (PC145D1043) is used to cover the leads (i.e., electrical interfacing) connecting the converter-charger to the thruster.

### 2.5 LIST OF THRUSTER DRAWINGS PRESENTED

Table 1 presents a list of drawings of the components to which the discussion of Section 2.1 through Section 2.4 has referred to. Tentative versions of the drawings which define the final design are presented in Appendix C of this report. The final version of these drawings will freeze the design during Task III - Model Specification.



TABLE 1. THRUSTER DRAWINGS PRESENTED

<u>Drawing Number</u>	<u>Figure Number</u>	<u>Description</u>
PC145D1010	9	Housing Assembly
PC145D1013-1	10	Forward Mount
PC145D1013-2		Aft Mount
PC145D1015	11	Bulkhead Assembly, Enclosure
PC145D1020	12	Capacitor Case Assembly, Case, Cover
PC145D1023	13	Collector Plate, Negative
PC145D1025	14	Standoffs, Thermal
PC145D1026	15	Insulators
PC145D1032	16	Electrode-Positive
PC145D1033	17	Collector Plate-Positive
PC145D1034	18	Mykroy Insulator
PC145D1036	19	Electrode Negative
PC145D1037	20	Insulator, Mykroy Sides
PC145D1040	21	Beam Assembly, Covers, End Closure
PC145D1043	22	Electrical Interface Cover
PC145D1050	23	Forward Faceplate Assembly
PC145D1051	24	Rear Faceplate Assembly
PC145D1052	25	Shield
PC145D1063	26	Bridge
PC145D1064	27	Transformer Base
PC145D1071	28	Delay Pulse Generator Board Assembly
PC145D1072	29	Delay Pulse Generator Drill Drawing
PC145D1073	30	Delay Pulse Generator Artwork
PC145D1075	31	Pulse Driver Assembly
PC145D1076	32	Pulse Driver Drill Drawing
PC145D1077	33	Pulse Driver Artwork
PC145D1080	34	Exhaust Cone Assembly
PC145D1090	35	Capaciter, SCD
PC145D1091	36	Igniter Plug, SCD
PC145D1092	37	Alignment Mirror

PRECEDING PAGE BLANK NOT FILMED

### 3.0 POWER CONDITIONER DESIGN

A detailed description of the operation as well as details of the components selected and a reliability analysis of the components of the Power Conditioner were presented in Reference 1. The Power Conditioner was designed and built for Fairchild Industries by Wilmore Electronics, Inc., to Fairchild Specification PC145S8000 (PC004S8000). The electrical acceptance pre-installation test of the power conditioner will be in accordance with Fairchild Specification PC145S8018 (see Appendix D). This report will only present drawings of the aforementioned design.

### 3.1 LIST OF POWER CONDITIONER DRAWINGS PRESENTED

Table 2 presents a list of the tentative drawings of the power conditioner. These drawings are presented as Figures in Appendix D of this report.

TABLE 2. POWER CONDITIONER DRAWINGS PRESENTED

<u>Wilmore Electronics Drawing Number</u>	<u>Figure Number</u>	<u>Description</u>
12C0050	38	Subassembly High Voltage Power Conditioner
12C0051	39	Subassembly Delay Trigger Generator
12C0052	40	Subassembly Auxiliary Power Supply
12C0053	41	Subassembly Comparator Regulator
12C0056	42	Subassembly Power Transformer
15C0190	43	Drill Drawing for 15C0181
15C0191	44	Drill Drawing for 15C0182
15C0192	45	Drill Drawing for 15C0185
15C0193	46	Drill Drawing for 15C0188
15C0194	47	Drill Drawing for 15C0189
16C0127	48	Schematic for Subassembly 12C0051
16C0128	49	Schematic for Subassembly 12C0052
16C0129	50	Schematic for Subassembly 12C0050
16C0130	51	Schematic for Subassembly 12C0053
16C0131	52	Converter Schematic
40D0212	53	Enclosure
40C0213	54	Cover

PRECEDING PAGE BLANK NOT FILMED

#### 4.0 SUPPLEMENTARY SUPPORTING STUDIES

During the design effort of Task 2 some additional design supporting studies were performed. The results of these studies are presented below.

##### 4.1 SIMULATED HI-G ACCELERATION THRUSTER OPERATION

Section 2.2.1.3 of the Task I report (Reference 1) presented results of a simulated 24.6 g load thruster test performed prior to contract award. The latter test was terminated after 1,200,254 consecutive discharges because of vacuum pumping difficulties. Since the engineering thermal model (Figure 22 of Reference 1) was available during Task 2, it was provided with three SH12K36 Negator springs laminated to provide a 17 lb. force. With an initial teflon propellant weight of 408.2276 grams the simulated initial g loading of the propellant rod against the 0.050 in. high fuel retaining shoulder in the positive electrode is thus 18.8 g's (prior to the test being reported upon the system was checked with the fuel bar weighing 455.1870 grams, i.e., a simulated 17 g's). The engineering thermal thruster model with the high spring force was installed on a thrust balance in a vacuum chamber (see Figure 55) and subsequently operated continuously for 1293 hours.




Figure 55. Simulated Hi-g Test on Thrust Balance

Unlike in spaceflight, as propellant is consumed in the laboratory, because of the fixed spring force, the simulated g force increases rather than decreases. The simulated Hi-g test performed is thus a more severe test than will be encountered in flight. Table 3 presents data of the test.

TABLE 3. SIMULATED HI-G TEST (LOG 136-4)

Initial propellant weight	408.2276 gr
Final propellant weight	234.6658 gr
Initial g loading	18.8
Final g loading	33
Test average pulse frequency	1.84 Hz
Total shots of test	8,578,289
Test duration of uninterrupted operation	1293 hours
Test average thrust measured	41.43 micro lb
Test average impulse bit amplitude	22.48 micro lb-sec
Test average specific impulse	505 sec

The test average thruster performance is in accordance with predicted behavior and within program requirements. During the 1293 hours of hi-g operation a total of 51 thrust readings were taken. The data presented above represents the test average of these readings. Of these, 8 readings fell below a  $20\mu$  lb-sec impulse bit level. The reason for these 8 readings being below  $20\mu$  lb-sec is not known. Since such a behavior has not been observed before with this particular electrode geometry and since the test average results are as predicted and within program requirements, the observed anomaly is only noted at this time.

The test was terminated because of failure of an ESXPJ20002 capacitor. Failure of the capacitor was in accordance with expected life. The history of earlier tests of this family of capacitors is as follows:

SN 13	14,703,251 discharges to failure
SN 14	15,041,970 discharges to failure
SN 15	14,884,282 discharges to failure (High g test)
SN 16	14,545,663 (still ok)

SN 15 and SN 16 used during the present test had discharges accumulated from prior tests. The ESXPJ20003 capacitor to be used in deliverable hardware is a derated version of the ESXPJ20002 that was used during the above test. Furthermore, the flight capacitor will not have the DC life superimposed which the above capacitors were subjected to.

A post test examination of the propellant and electrode assembly was made. No abnormalities were observed which would suggest the system becoming inoperative before the design life expectancy. Figure 56 shows a front view of the thruster after the simulated hi-g test. Figure 57 shows the anode with a slight deposit on it. The cathode is shown in Figure 58. A relatively heavy deposit is noted on the cathode and in particular around the igniter plug area. Such deposits are normally observed on the cathode. The propellant revealed no signs of discoloration or abnormal depolymerization.

The above test results are considered highly encouraging that the final design will meet all performance, life and environmental requirements of the SMS mission.



Figure 56. Post Hi-g Test Frontal View






Figure 57. Anode of Hi-g Test



Figure 58. Cathode of Hi-g Test



reacted at the support. If the clip is .100 inch thick and .750 inches wide, this moment causes a bending stress of 95000 psi. Since the bending yield for 6061 T6 aluminum is 35000 psi this clip should be designed for higher stiffness, i.e., thicker section or channel shape. However, if the tie-down points are moved further apart so that they are directly under the housing skin, the problem of the bending moment is eliminated while at the same time provision can be made for external access to the mounting fasteners. Thus, it is recommended that the mounting holes be placed about 7.3 inches on center and the housing skin be tied to a mounting bracket with five rivets on the side and five rivets on the bottom. These .093 diameter rivets will cause a maximum bearing stress of 11300 psi which is well below the bearing yield of 50000 psi. The maximum shear stress is 3100 psi. A request for the change was submitted to Mr. Williams of GSFC for approval. The proposed increase was approved by NASA TD112 and was subsequently incorporated in the design (see Figure 3 ).

#### 4.3 FURTHER STRUCTURAL CONSIDERATIONS OF VIBRATION ENVIRONMENT

In order to ascertain whether the microthruster will sustain the qualification vibration tests without failure, it is important to know the resonant frequencies and modes associated with it. For this purpose the thruster was considered as a simply supported beam with six lumped masses. The flexibility of the microthruster in a direction perpendicular to the mounting surface (the direction in which the microthruster is most flexible) was represented by an EI distribution along the beam. A set of influence coefficients was derived and used in a matrix iterative procedure to obtain the modes and frequencies.

The frequency of the first mode 3370 Hz is far above the 2000 Hz limit of the vibration test. Thus, although beam representation of the microthruster is a very simplified one in which effects of rotary inertia and motion in orthogonal directions are neglected, the high frequency of the first mode indicates that in the shake test no flexible mode involving motion of the whole assembly will have a frequency below 2000 Hz. Under this condition there will be no amplification in response to the input g levels. However, there may be localized resonances of lower frequency involving significant masses which are not uncovered by the beam analysis. Accordingly, several simplified calculations have been made to obtain an estimate of these frequencies. The results of these analyses indicate that for any resonance in which

there is motion of a component with significant mass the frequency should exceed 100 Hz. Some sample frequency calculations are shown below. The sinusoidal test schedule calls for a maximum level of 5 g for frequencies above 100 Hz (i.e., from 200 to 2000 Hz). If the critical damping ratio for any resonance is assumed to be .03 or greater and if it is understood that at any resonant frequency only part of the total microthruster mass will be moving, the load at the support points should never exceed that which would exist for the equivalent of 50 g at the overall center of gravity. For this condition assuming inertia loading in the vehicle thrust direction the most highly stressed point will be the bottom of the rear support bracket. This stress, 21646 psi, in bending is well below the yield for 6061TG which is 35000 psi.

During the random vibration test the input level corresponds to 9.2 g rms. To this there is some added effect due to peaks clipped at 3 times specified levels and due to amplification of local resonances in the 20-2000 Hz range. Even with these added effects the overall level at the support should be well below 50 g.

Consequently the microthruster is expected to survive the random and sinusoidal vibration tests without failure.

#### 4.3.1 Fore and Aft Motion of Capacitor

For simplicity the capacitor is assumed to be restrained only by the 7 spokes of the fiberglass faceplate (PC145D1050). The spokes are taken as cantilevered with a concentrated load representing 1/7 the mass of the capacitor at one end.




Figure 59. Idealized Spoke of Faceplate

$$f = \frac{1}{2\pi} \sqrt{\frac{k}{m}} = \frac{1}{2\pi} \sqrt{\frac{3EI}{m\ell^3}} = \frac{1}{2\pi} \sqrt{\frac{3(2.5) 10^6 (.06) (.38)^3 386.}{.22 (12) (.88)^3}} = 366 \text{ Hz}$$

The calculated frequency  $f = 366 \text{ Hz}$  will tend to be reduced because the ends of the spokes are not quite cantilevered. On the other hand, the frequency  $f$  will tend to be raised due to the added support of the stiffening "zee" sections (PC145D1012) and the supporting structure at the aft end of the capacitor. In any case it should be reasonable to assume that the actual frequency will be above 100 Hz.

#### 4.3.2 Rear Main Thruster Mount

The base of the rear main mount is a flat surface 1.1 by .63 inches and .1 inch thick supported on three sides. A 1 g vertical load on the microthruster would result in a load of approximately 3.8 pounds at the rear support. The following simplified calculations use case No. 50 in Reference 2.

The maximum deflection for a uniformly distributed load is:

$$y = \frac{\alpha \omega a^4}{Et^3}$$

where:  $\alpha = .09$  for a long side to short side ratio of 1.8

If we use a factor of 1/1.6 as the approximate ratio for deflection under uniform load to deflection under the actual concentrated load, the deflection is:

$$y = \frac{1.6 (.09) 5.59 (1.1)^4}{(10^7) (.1)^3} = 1.1785 \cdot 10^{-4}$$

The approximate frequency corresponding to this deflection is:

$$f \approx 314 \sqrt{\frac{10^4}{1.1785}} = 289 \text{ Hz}$$

This is a very approximate frequency calculation. However, it is reasonable to conclude that the actual frequency will be greater than 100 Hz. According to Ruark the maximum stress associated with the above loading is:

$$\frac{\beta \omega a^2}{t^2}$$

If we assume a 50 g loading and increase the stress by the 1.6 factor and use a value of .4 for  $\beta$ , the maximum stress is:


$$\frac{1.6 (.4) 50 (5.59) (1.1)^2}{(.1)^2} = 21646 \text{ psi}$$

This is well below the 6061-T6 yield of 35000 psi.

#### 4.3.3 Exhaust Cone

The thruster exhaust cone (PC145D1080) is a small part of the total mass so that any resonances which are excited on the cone will have negligible effect on the overall loading at the main thruster supports. However, it is necessary to ascertain whether local stresses will cause failure of the cone itself.

Consider one side of the exhaust cone. It has the approximate shape shown in Figure 60a.



a) Approximate Cone  
Surface Shape

b) Idealized Cone Shape

Figure 60. Cone Surface Configuration

We can approximate this shape as a rectangular flat plate supported on three sides as shown in Figure 60b with a .030 inch thick layer of Mykroy on a .030-inch thick aluminum substrate.

Assume that the Mykroy contributes mass but not stiffness, then the maximum deflection is:

$$y = \frac{\alpha \omega a^4}{Et^3}$$

where:

$\alpha$	=	.12
$E$	=	$10^7$
$t$	=	.03
$a$	=	3.2
$\omega$	=	.006 lbs/in. <sup>2</sup>

$$y = \frac{.12 (.006) (3.2)^4}{10^7 (.03)^3} = .0002796 \text{ inches}$$

and the frequency is thus:

$$f = 3.140 \sqrt{\frac{1}{279.6}} = 188 \text{ Hz}$$

The latter frequency is also above 100 Hz.

#### 4.4 WEIGHT CONSIDERATIONS

During Task II the design has advanced to the point where a more accurate revised systems weight estimate can be made. Based upon presently available data the total propulsion system weight (including propellant) will be about 4142 grams (9.13 lb). This weight is made up of 3292 grams (7.26 lb) for the thruster sub-assembly and 850 grams (1.87 lb) for the power conditioner subassembly. Table 4 presents a further breakdown of the thruster weight by major and minor assemblies as best as can be determined at this time.

Every attempt has been made in the design of Task 2 to keep the weight of every item at an absolute minimum. The extra design and fabrication effort required to achieve minimum weight can be noted for example by an examination of the items presented in Figure 4.

TABLE 4. BREAKDOWN OF REVISED THRUSTER WEIGHT

<u>Major Item</u>	<u>Minor Item</u>	<u>Item Weight (grams)</u>	<u>Total Weight (grams)</u>
a) <u>Structural</u>			
	Bulkhead with studs	108.4	
	Housing	142	
	Bulkhead inserts	6.5	
	Forward mounts	30	
	Aft mount	19.8	
	Z	55	
	Electrical cover	35	
	Insulated mounts	9.4	
	Subtotal	406.1	
b) <u>Fuel Subassembly</u>			
	Beam	126.5	
	End cover	11	
	Top cover	21.5	
	Fiberglass box	30.0	
	Usable fuel	400	
	Spring assembly	28	
	Subtotal	617	
c) <u>Thruster Electronics</u>			
	Entire package	441	
d) <u>Discharge Subassembly</u>			
	Faceplate with positive collector plate, electrode	255	
	Negative electrode subassembly	78	
	Can subassembly	94.5	
	Can covers	33.2	
	Capacitor	1197	
	Subtotal	1657.7	
e) <u>Miscellaneous</u>			
	Cone with Mykroy	110	
	Paint	50	
	Mirror	4	
	Screws, etc.	6.2	
	Subtotal	170.2	
f) <u>Power Conditioner</u>			
	Complete	850	
Estimated Total System Weight• . . . . .			4142

## 5.0 PROGRAM FOR NEXT REPORTING PERIOD

The next reporting period will provide the Task B "Model Specification". The design described in the present Task 2 report will be frozen upon completion of Task 3 effort. The Task 4 effort "Final Fabrication and Test" will be initiated prior to completion of the Task 3 effort.

## 6.0 CONCLUSIONS

The results presented herein have shown that inherent functional simplicity underlying the flight proven LES-6 design can be maintained in the SMS system design even with minimum weight constraints imposed. Furthermore, a 1293 hour uninterrupted vacuum test with the engineering thermal model simulating an 18.8 to 33 g environment of the propellant, its fuel system and electrode assembly revealed that program thruster performance requirements could be met. This latter g environment is a more severe environment than will be ever encountered in the SMS spacecraft. Best available data at this point indicates that the completed propulsion system weight including propellant will be about 9.13 lbs.

## 7.0 REFERENCE MATERIAL

### 7.1 REFERENCES

1. "Task 1 - Design Analysis Report, Pulsed Plasma Solid Propellant Microthruster for the Synchronous Meteorological Satellite,"  
Edited by W.J. Guman, Interim Report on Contract NAS5-11494,  
PCD-71-7, PC145R8000, FRD 4070, Fairchild Industries, Fairchild  
Republic Division, Farmingdale, New York.
2. Roark, R.J., "Formulas for Stress and Strain, McGraw Hill Book Co.,  
N.Y. 1938.

### 7.2 APPENDICES

APPENDIX A. LIST OF APPLICABLE DOCUMENTS

<u>Fairchild Document</u>	<u>Item</u>	<u>Type of Specification</u>
PC004S8000 PC145S8000	Power Conditioner	Product
PC145S8001	Energy Storage Capacitor	Product
PC145S8002	Capacitor B161Y203-302K	Screening
PC145S8003	Capacitor 118P10591032	Screening
PC145S8004	SCR C137PB1200	Screening
PC145S8005	Negator Spring	Product
PC145S8006	Diode UT2080	Screening
PC145S8007	Pulse Transformer 8TE5904E	Product
PC145S8008	Surface Igniter Plug 10-380729-1 Change A-4	Product
PC145S8009	Negator Dry Film Lubricant	Material & Process
PC145S8010	Thermistor RTH06BS472J	Screening
PC145S8011	Pulse Transformer	Screening
PC145S8012	Surface Igniter Plug	Pre-Instal. Test
PC145S8013	Thruster Capacitor	Pre-Instal. Test
PC145S8014	Cone High Pot. Test	Pre-Instal. Test
PC145S8015	Pulse Driver Circuit Board	Pre-Instal. Test
PC145S8016	Delay Trigger & Flip Flop	Pre-Instal. Test
PC145S8017	Discharge Initiating Circuit	Pre-Instal. Test
PC145S8018	Power Conditioner	Pre-Instal. Test
PC145S8019	Front Assembly Hi-Pot Test	Pre-Instal. Test
PC145S8020	Qualification Sinusoidal & Random Vibration	Qualification Test



APPENDIX B. SAMPLE SPECIFICATION

August 10, 1971  
PC004S8000

FAIRCHILD INDUSTRIES, INC.  
Fairchild Republic Division  
Power Conversion Department

Product Specification for:  
SMS POWER CONDITIONER

Prepared by: Robert Gelbman  
R. Gelbman PCD

Approved by: William J. Guman  
W. J. Guman, Program Manager

## POWER CONDITIONER SPECIFICATION

### 1. SCOPE

1.1 This specification describes an energy conversion system specifically tailored for the SMS Satellite mission. The energy conversion system is hereafter referred to as the Power Conditioner.

### 2. APPLICABLE DOCUMENTS

- a. Requirements for Soldered Electrical Connections, NHB 5300.4 (3a) May, 1968
- b. Inspection System Provisions for Suppliers of Space Materials, Parts, Components, and Services; NPC 200-3, April 1962
- c. Printed Wiring Boards, S-300-P-1A October 1966
- d. General Environmental Test Specification for Spacecraft and Components GSFC S-320-G-1, October 1969
- e. Connectors Subminiature, Electrical and Coaxial Contact, for Space Flight Use; GSFC S-311-P-10, April 1, 1970
- f. GSFC Preferred Parts List, GSFC PPL-11, July 1970
- g. Contractor Malfunction Reporting, GSFC S-312-P-1, March 1970
- h. Requirements for Photographic Documentation S-253-P-4 (Still Photography)

### 3. REQUIREMENTS

#### 3.1 General Requirements

##### 3.1.1 Main Capacitor Load

The power conditioner shall perform the function of charging a capacitor load to a predetermined high voltage without warm-up time within the scope of the specifications enumerated elsewhere in this document.

##### 3.1.2 Auxiliary Capacitor Load

The power conditioner shall perform the function of charging an additional capacitor load to a predetermined intermediate voltage without warm-up time within the scope of the specifications enumerated elsewhere in this document.

### 3.1.3 Telemetry and Hardware Monitors

The power conditioner shall also perform the function of supplying telemetry signals and hardware monitors as enumerated elsewhere in this document.

3.1.4 There shall be no function adjustment screws allowed on the power conditioner.

## 3.2 INPUTS

### 3.2.1 Primary Power

Primary power will be supplied from a regulated solar array bus having an output voltage within the range of 29.4 volts  $\pm$  0.2 volts DC. The output impedance of this source is 0.5  $\Omega$  maximum, 0.2  $\Omega$  typical from DC to 50 KHz. The power conditioner will function normally with this input source of power. Maximum Input Power design goal: 20 watts @ 110 RPM (1.833 charge cycles/sec).

### 3.2.2 Housekeeping

3.2.2.1 The 29.4 volt solar array bus voltage will be continuously applied to the power conditioner. A separate 28 volt  $\pm$  2.0 volt enable signal from a 200 ohm source impedance will be applied to energize the power conditioner. The power conditioner will be on when this signal is 28 volts  $\pm$  2 volts D.C. and will be off when the signal is 0 volts  $\pm$  1.2 volts D.C. from a 5000  $\Omega$  source impedance. Current drain from this source shall be 0.5 ma maximum.

### 3.2.2.2 Fire Command Signal

The Fire Command Signal shall be defined as follows:

- a. Logic One (Command Level) +5.0 volts  $\pm$  0.5 volts DC
- b. Logic Zero (Ground Level) 0.0 volts  $\pm$  0.5 volts DC
- c. Duration: 50 milliseconds  $\pm$  5 milliseconds
- d. Repetition Rate: 0.5454 second to 1.2 second (.833 pulse/sec to 1.833 pulses/sec)
- e. Rise and Fall times - Greater than 2 microseconds and less than 10 microseconds

The impedance on the Fire Command Line shall be 10 K $\Omega$  minimum. The power conditioner shall be capable of continuously receiving Fire Command Signals while power source is turned off. Upon application of power the power conditioner shall begin normal operation. Turning the power source on and off shall be considered a normal operating mode.

### 3.3 OUTPUTS

3.3.1 The power conditioner shall be capable of charging two (2)  $4.0\mu\text{fd} \pm 5\%$  capacitors, connected in parallel, to 1450 volts  $\pm 1\%$  in 500 milliseconds  $\pm 40$  milliseconds over a temperature range  $-20^{\circ}\text{C}$  to  $+60^{\circ}\text{C}$  in air or in a vacuum with a base plate temperature of  $-20^{\circ}\text{C}$  to  $60^{\circ}\text{C}$ . The capacitor charge time shall not in any case exceed 540 milliseconds with 29.4 volts  $\pm 0.2$  volts input. The change in capacitance with temperature shall be about  $+1\%$  at  $140^{\circ}\text{F}$  and  $-4\%$  at  $-40^{\circ}\text{F}$ .

3.3.2 The power conditioner shall also supply an output capable of charging two (2)  $1.0\mu\text{fd} \pm 5\%$  capacitors connected in parallel to 620 volts  $\pm 20$  volts DC in the charge time specified herein (i.e., 3.3.1.).

#### 3.3.3 Pulse Rate Sensing

The power conditioner shall be capable of sensing the Fire Command pulse rate such that, at the maximum pulse rate (110 ppm), the recharging of the energy storage capacitor begins almost immediately after each thruster firing, but at lower pulse rates ( $50 \leq \text{pulse rate} \leq 110$ ) the initiation of recharging will be delayed before the next fire pulse.

The duration of this delay is pulse frequency dependent. (See Figure 1.) The hold off time, is defined as the time interval after full output voltage is attained up to the time of thruster firing. Hold off time shall be greater than 5 milliseconds and less than 50 milliseconds. The pulse rate adjustment circuit shall be capable of adjusting the hold off time such that it does not exceed 55 milliseconds within 30 seconds after the power conditioner has been turned on or after the satellite has changed its spin rate.

#### 3.3.4 Duty Cycle

The power conditioner must be capable of operation at a maximum rate of 110 cycles per minute. When the load capacitors are charged, the power conditioner high voltage outputs must be maintained at  $1450 \pm 1\%$  and  $620 \pm 20\text{V}$  respectively for any worst case combinations of input voltage and environment until a firing command pulse causes thruster firing. If the 620 volt output should be discharged while the 1450 volt is not, both the 620 V and 1450V shall be restored in the next charge cycle.

3.3.5 The power conditioner shall supply + 12 VDC  $\pm$  0.5V at 25 ma and 29.4 volts to the control logic when the enable signal energizes the power conditioner.

3.3.6 The power conditioner shall also supply the fire command signal to the control logic. The power conditioner shall present 100 K $\Omega$  minimum impedance to the fire command pulse.

#### 3.3.7 Telemetry Outputs

Four (4) telemetry channels shall be provided as follows:

- a. Enable signal: 0 to + 32 volts
- b. Main capacitor voltage: 0 to 1.2 times nominal
- c. Discharge initiation capacitor voltage: 0 to 1.2 times nominal
- d. Mean internal thruster temperature: -50°F to + 150°F

The telemetry output signals shall be between zero and +5 volts. Each channel shall contain limiting circuitry so that the output signal can go to + 5.5 volts maximum and -0.7 volts minimum. The telemetry maximum output impedance of any channel shall be 1000 ohms or less. The cutoff (3 db down) frequency for the voltage measurements shall be about 150 Hz. Sufficient isolation shall be provided in the telemetry circuits such that shorting an output to ground or to any other telemetry output shall not damage the telemetry circuitry or affect in any manner the operation of the microthruster. EMI filters are required on these outputs.

#### 3.3.8 Hardwire Monitors

A system of hardwire monitors is desired to supply detailed information during qualification tests and other ground tests. These shall consist of individual monitor leads connected directly to key points in the circuitry. All of these monitors shall be brought out to a single connector mounted on the housing. (See Figure 2.) As a minimum the following conditions shall be monitored:

- a. Thruster supply voltage
- b. Energy storage capacitor voltages
- c. Charger enable signal
- d. Firing command input to the discharge initiation circuit.

The contractor shall review his design and make recommendations as to what additional functions should be monitored. EMI filters are not required on these outputs.

### 3.4 PROTECTION

#### 3.4.1 Short Circuit Protection

The power conditioner shall not sustain damage when operating into a short circuit in any of the load capacitors for sustained periods under all operating conditions specified herein.

#### 3.4.2 Open Circuit Protection

The power conditioner shall be protected from operation without a capacitor load by an externally mounted capacitor which is to be removed before the power conditioner is hard wired to the thruster.

#### 3.4.3 Bleeders

In the event that any or all of the output loads of the power conditioner fail(s) to be discharged following power conditioner de-energizing, the 1450 load voltage will discharge through bleeders and/or leakages to less than 73 volts in 30 minutes or less.

### 3.5 ENVIRONMENTAL CONDITIONS

The power conditioner shall be designed to meet the following requirements

#### 3.5.1 Shock

Three 850-g, 0.2 millisecond impacts along each of three orthogonal axes one of which is parallel to the spacecraft thrust axis.

#### 3.5.2 Humidity

The power conditioner shall be installed in a temperature and humidity chamber where the atmospheric condition in the immediate vicinity of the power conditioner is as follows and in which the air is constantly circulated by a fan:

- a. Temperature:  $86^{\circ}\text{F} \pm 4^{\circ}\text{F}$
- b. Relative Humidity:  $90\% \pm 3\%$

After stabilization, the power conditioner shall be exposed to the foregoing conditions for 24 hours. Subsequently the power conditioner shall be operated and its performance checked.

### 3.5.3 Vibration:

The power conditioner shall be attached to the vibration generator via a rigid fixture. Attachment of the power conditioner to the fixture shall simulate the actual attachment of the power conditioner to a spacecraft structure. Vibrations shall be applied in each of three orthogonal directions, one direction being parallel to the spacecraft thrust axis.

### 3.5.4 Sinusoidal - Swept Frequency

This portion of the test shall be conducted by sweeping the applied frequency once through each range specified in the schedule. The rate of change of frequency shall be two octaves per minute.

#### Sinusoidal Vibration Schedule

<u>FREQUENCY (Hz)</u>	<u>LEVEL</u> (g, 0 to peak)	<u>AXIS</u>
5 - 10	0.5" DA(double amplitude)	Lateral X-X, Y-Y (Launch vehicle lateral)
10 - 20	14.0	
20 - 100	4.0	
100 - 200	2.0	
200 - 2000	5.0	
5 - 11	0.5" DA(double amplitude)	Perpendicular to mounting plane (Launch vehicle thrust)
11 - 17	3.0	
17 - 23	7.0	
23 - 30	12.5	
30 - 60	25.0	
60 - 80	8.0	
80 - 200	3.0	
200 - 2000	5.0	

NOTE: Sweep rate is 2 octaves/minute for all spectra

### 3.5.5 Random Motion Vibration

Gaussian random motion vibration shall be applied with the g-peaks clipped at three times the rms acceleration specified in the schedule

#### Random Motion Vibration Schedule

<u>Frequency</u> (Hr)	<u>Acceleration</u> (g-rms)	<u>Test Duration</u> (minutes per axis)	<u>PSD LEVEL</u> (g <sup>2</sup> /Hz)
20-150	9.2	4	0.0225
150-300	9.2	4	Increasing from 150 Hz at constant rate of +3db
300-2000	9.2	4	0.045



### 3.5.6 Prelaunch Environment Conditions

The power conditioner shall not suffer detrimental affects from exposure to the following prelaunch environmental conditions:

- a. Temperature:  $75^{\circ}\text{F} \pm 5^{\circ}\text{F}$
- b. Relative Humidity: 50 percent maximum
- c. Duration: 3 weeks

### 3.5.7 Storage Temperature Condition

The power conditioner shall suffer no detrimental affects from exposure to temperatures in the range of  $0^{\circ}\text{F}$  to  $130^{\circ}\text{F}$  for storage durations of up to 3 years.

### 3.5.8 Attitude

The power conditioner shall be capable of operating in any attitude at 1-g or 0-g and shall be capable of operating after storage in any attitude at 1-g for three years.

3.5.9 The contractor shall design the power conditioner to operate as specified within the following operating environments.

3.5.10 Acceleration: The power conditioner shall be required to operate as specified under a sustained acceleration of thirteen (13) g's applied in the same direction as the plasma exhaust for a period of 5 years. Proper operation shall be possible at loads equivalent to 20 g's.

3.5.11 Temperature: The power conditioner shall be required to operate as specified when exposed to vacuum conditions with the temperature of the mounting structure and all of the surrounding surfaces (except where portions of the thruster are exposed to space) in the range from  $0^{\circ}\text{F}$  to  $140^{\circ}\text{F}$  as a steady state temperature or cycling between the extremes with a cyclic period greater than or equal to 6.2 hours.

3.5.12 Pressure: The power conditioner shall be required to operate as specified when the ambient pressure is less than  $5 \times 10^{-5}$  Torr. The power conditioner shall be designed to operate as specified when simultaneously exposed to the environments delineated above.

3.5.13 Reliability: High reliability is a prime requirement of this system. Simplicity of design shall be considered in the design. Particular emphasis shall be placed on those materials, techniques and components which offer high reliability and long life for spacecraft application.

3.5.14 Safety: The power conditioner shall be designed to minimize the hazard of electrical shock, fire and explosion on the spacecraft and during ground test.

3.5.15 Noise Susceptibility: The operation of the power conditioner shall not be disturbed nor performance degraded when the system is subjected to RF fields in the VHF-UHF band of as much as one volt per meter adjacent to the power conditioner. In addition, the system shall perform within specification when as much as one volt peak noise of 15 to 100 microseconds bursts is fed into the power supply bus.

3.5.16 Grounding: The circuit ground and chassis ground shall be maintained separately. The number of tie points for command return, telemetry return, and power return shall be minimized to preclude the possibility of ground loops.

3.5.17 EMI: Conducted EMI on the power bus, telemetry lines and command lines shall be kept as low as possible. All lines interfacing with the spacecraft shall contain EMI line filters. In addition, conducted and radiated EMI measurements shall be made at the spacecraft command and telemetry frequencies. VHF (135-149 MHZ) VHF (400-470 MHZ) S BAND (1670-2035 MHZ).

3.5.18 Connectors: Only two connectors shall be used on the power conditioner. One shall be provided for the spacecraft interface and the other for the hardwire (test points) interface. Both connectors shall adhere to the requirements of S-320-G-1 and GSFC S-311-P-10. Mating connectors shall be defined and disclosed to Fairchild Industries as soon as the connectors to be used on the power conditioner have been specified by the contractor, but in any case the disclosure shall be made no later than December 1, 1971. Extra pins on the connectors shall be used to double up on critical inputs such as SUPPLY VOLTAGE, ENABLE SIGNAL and the FIRE COMMAND SIGNAL.

### 3.6 DOCUMENTATION:

3.6.1 The drawings and documentation for the power conditioner shall be in accordance with the contractors standard engineering practice including the contractors release and control system. A bill of materials, in the contractors standard format, itemizing each component, subassembly and assembly drawing shall be provided.

The drawings and documentation, including the bill-of-materials, shall be of sufficient detail and of the type to:

- a) Enable manufacture of the power conditioner, its subassemblies, components, etc
- b) Procure components, subassemblies and assemblies for testing as may be required
- c) Conduct failure analysis as may be required.

3.6.2 The contractor shall deliver with each flight prototype model power conditioner the following:

- a) A complete updated set of engineering drawings
- b) An operation/maintenance manual
- c) Revisions to the model specification(if required)
- d) A complete updated set of top-assembly and sub-assembly records
- e) A preliminary report of the test data resulting from the ATP.

3.6.3 The contractor shall supply at least one photograph per S-253-P4 (STILL PHOTOGRAPHY).

### 3.7 MODEL SPECIFICATION

3.7.1 The contractor shall prepare and deliver a model specification of the flight prototype model power conditioner as specified herein. The model specification shall define all of the power conditioners operating parameters including

- a) Weight
- b) Size
- c) Thermal Requirements and restraints
- d) Mechanical Requirements and restraints
- e) Interface Requirements and restraints
- f) Electrical/Electronic Requirements and restraints
- g) Performance requirements

This model specification is due at Fairchild Industries no later than November 25, 1971.

### **3.8 PARTS AND MATERIAL**

3.8.1 Where possible, parts shall be selected per the GSFC Preferred Parts List, PPL-II. Parts selected for use on this program which do not appear on the GSFC PPL will be considered non-standardized and will require written approval by the GSFC Technical Officer for their intended use. All electronic parts will be screened, as a minimum, in accordance with the provisions of Appendix C of the GSFC PPL. The parts and materials list shall be submitted to Fairchild Industries with a copy to the GSFC Technical Officer for review thirty days prior to purchase of parts or release of drawings for fabrication.

### **3.9 TEST DATA**


3.9.1 The power conditioner shall be tested by the contractor to verify its electrical performance to this specification. These tests shall consist of operation at low temperature (about 0° F), high temperature (about 140° F) and at room temperature (about 68° F) with data being taken at all three temperatures. The power conditioner shall accumulate at least 5 hours of operation before shipment to Fairchild Industries, Inc.

3.10 Weight: 698 GRAMS DESIGN GOAL 800 GRAMS MAXIMUM

3.11 DIMENSIONS: The power conditioner shall fit within the outlines of Fig. 2.


3.12 DESIGN LIFE: No design technique shall be used which would result in less than  $20 \times 10^6$  charge discharge cycles.

3.13 MOUNTING PROVISIONS : The power conditioner shall be supplied with mounting provisions to be specified by Fairchild Industries soon after the inception of the program.



CAPACITOR VOLTAGE VS. TIME FOR  
LOW SPIN RATE WITH PULSE RATE SENSING.

FIGURE 1



OUTPUT CONNECTIONS TO THRUSTER PACKAGE  
PREFERABLY WITHIN THE SHADED OUTLINES.

FIGURE 2

The following is Fairchild Industries/Fairchild Republic Division (FI/FRD) criteria for the derating of SMS Microthruster electronic, electrical and electro-mechanical parts. This criteria is a guide to ensure high inherent reliability and to prolong the useful life of parts. Exceptions to the criteria are permitted when based on sound engineering principles and judgment and with the written approval by FI/FRD.



Table 01. Derating Outline For Capacitors

Dielectric Class	Derate To	Remarks
Ceramic	50% of rated voltage	All capacitors: Except as noted below, capacitors shall not be used at ambient temperatures exceeding 85°C. The design shall also provide proper derating of capacitors operated under AC, pulse or transient voltages specified in applicable specifications.
Mica (Dipped)	60% of rated voltage	
Mica (Molded)	40% of rated voltage	
Paper	50% of rated voltage	
Mylar	75% of rated voltage	
Glass or Porcelain	50% of rated voltage	Ambient temperature shall not exceed 50°C.
Tantalum (Solid electrolytic) 3 ohm/volt surge limiting resistor	60% of rated voltage	
0.1 ohm/volt surge limiting resistor	40% of rated voltage	
Tantalum (Wet electrolytic)	70% of rated voltage	{ Ambient temperature shall not exceed 70°C.
Tantalum (Foil)	70% of rated voltage	

TABLE 02. DERATING OUTLINE OF CONNECTORS

Number of Contacts Used in Connector	Contact Size	Maximum Current per contact <sup>1/</sup> (Amperes)					Remarks
		Wire Size (AWG)					
		16	18	20	22	24	
1 to 4	16	13.0	9.2	6.5			All connectors: Maximum allowable operating voltage shall be 25% of the dielectric withstanding voltage rating for the anticipated environment.
1 to 4	20			6.0	4.5	3.3	
5 to 14	16	9.0	7.0	5.0			
5 to 14	20			5.0	3.5	2.7	
15 or more	16	6.5	5.0	3.7			
15 or more	20			3.7	2.5	2.0	

<sup>1/</sup> Maximum current may be carried by only 10% of the contacts at one time. At such time, other contacts should be limited to 100 mA.

TABLE 03. DERATING OUTLINE OF EMI FILTERS

Class	Derate To	Remarks
All Filters	50% rated feed thru current and 50% rated DC working voltage	Ambient temperature shall not exceed 85 C.

TABLE 04. DERATING OUTLINE OF FUSES

(e. g., Littelfuse "Picofuse" & Bussmann "Tron")

Fuse Current Rating (Amperes)	Derate to the following (%) of Rated Amperes <sup>1/</sup>	Remarks
5	50%	Derating of fuses allows for possible loss of pressure, which lowers the blow current rating and allows for a decrease of current capability with time.
2	50%	
1	45%	
1/2	40%	
3/8	35%	
1/4	30%	

<sup>1/</sup> Derating factors are based on data from fuses mounted on printed circuit boards and conformally coated.

Reproduced from  
best available copy.



TABLE 05. DERATING OUTLINE OF INDUCTORS AND TRANSFORMERS

Inductor Class per MIL-C-15305	Transformer Class per MIL-T-27	Maximum Operating 1/ Temperature (Ambient plus temp. rise)	Remarks
0	Q	65° C	Derate maximum winding voltage of all inductors and transformers to 50% of the manufacturers rated voltage.
A	R	85° C	
B	S	105° C	

- 1/ a) Maximum operating temperature equals ambient temperature + temperature rise + 10°C hot spot temperature  
 Temperature rise =  $\frac{R}{r}(T+234.5)$  — R, is the resistance of winding under load;  
 r, is the resistance of winding without load at ambient temperature, T
- b) The insulation classes of MIL style inductive parts have maximum operating temperature ratings which are generally based upon a life expectancy of at least 10,000 hrs. The maximum operating temperatures in this table are selected to extend the life expectancy by a factor of 5 beyond the MIL rating
- c) Custom made inductive parts should be evaluated on a materials basis and stressed at levels which give maximum operating temperatures well below the rated maximums of the materials used. These should be commensurate with the deratings shown above for standard devices.

TABLE 06. DERATING OUTLINE OF RELAYS

Class	Derate To	Remarks
All Relays	50% of rated contact current	Users should be cautioned not to reduce coil current or voltage below that re- quired for reliable operation.

TABLE 07. DERATING OUTLINE OF RESISTORS

Class	Derate To	Remarks
Carbon Composition (RCR)	50% of rated power	<b>All resistors:</b> a) Maximum voltage shall not exceed 80% of the maximum rated voltage on any resistor. b) When two or more resistors are mounted so closely that heat from one resistor influences ambient conditions of another, they should be derated by an additional factor of 0.5. c) Resistors with weldable nickel leads shall be derated by an additional factor of 0.5.
Film, General Purpose (RLR)	50% of rated power	
Film, High Stability (RNR)	50% of rated power	
Wirewound Accurate 1% Tolerance	50% of rated power	
0.5% Tolerance	35% of rated power	
0.1% Tolerance	25% of rated power	
Wirewound Power, chassis mount	30% of rated power	
Wirewound Power, (RWR)	50% of rated power	
Variable Trimmers	50% of rated power	

TABLE 08. DERATING OUTLINE OF DIODES

Class	Derate To*	Remarks
General Purpose Rectifier	50% of rated power 20% of rated power 50% of rated forward current	<b>All diodes:</b> a) Derating factors are based on a 25°C ambient temperature. *b) Junction temperature shall not exceed 65% of $T_{jmax}$ . c) Peak inverse voltage or transients shall not exceed 80% of manufacturers rated value unless otherwise stated.
Reference Diode	50% of PIV	
Switching Diode	20% of rated power	
Silicon Controlled Rectifier	20% of rated power 50% of rated forward current	
Zener	50% of rated power	

Reproduced from  
best available copy.



TABLE 09A. DERATING OUTLINE OF SILICON TRANSISTORS

Class	Derate To*	Remarks
Low Power NPN	20% of rated power	*Junction temperature shall not exceed 125°C for all applications. In the event of a conflict between this and the power derating factors, the 125°C limit shall govern. Breakdown voltage for all devices should be derated to 75% $BV_{ECO}$ , 75% $BV_{ENO}$ and 75% $BV_{CBO}$ .
Low Power PNP	20% of rated power	
High Power NPN	15% of rated power	
Switching NPN	20% of rated power	
Switching PNP	20% of rated power	
Unijunction	20% of rated power	

TABLE 09B. DERATING OUTLINE OF FIELD EFFECT TRANSISTORS (FET)

Class	Derate To*	Remarks
General Purpose	40% of rated power	*Junction temperature shall not exceed 125°C for all applications. Breakdown voltage for all devices should be derated to 75% $BV_{DSO}$ , 75% $BV_{DGO}$ and 75% $BV_{SGO}$ .
High Speed Switch	40% of rated power	
Medium Power	30% of rated power	
High Power	30% of rated power	

Reproduced from  
best available copy.



TABLE 10. DERATING OUTLINE OF INTEGRATED CIRCUITS

Class	Derate To	Remarks
Digital		
1. AC and DC Fan-Outs	60% of Manufacturer max rating	The Manufacturer's suggested bias voltages shall not be derated unless precautions are taken to assure that such action does not cause possible malfunction.
2. Combination of AC and DC Fan-Outs		
a) Load limits of AC levels	60% of Manufacturer max rating	
b) Load limits of DC levels	40% of Manufacturer max rating	

TABLE 14. DERATING OUTLINE OF THERMISTORS  
(Temperature Sensitive Resistor)

Class	Derate To	Remarks
All Thermistors	50% of rated power	

TABLE 15. DERATING OUTLINE OF TRANSFORMERS  
(See Table 05, Inductors and Transformers)

TABLE 16. DERATING OUTLINE OF WIRE AND CABLE

Derate to - Amps. max.			Remarks
Wire Size	Bundle or Cable	Single	
26	1.4	2.5	<p>1. Current ratings for bundles or cables are based on bundles of 15 or more wires at 70° C in a hard vacuum. In smaller bundles the allowable current may be increased as the bundle approaches a single wire.</p> <p>2. Ratings are based on Teflon insulated wire (Type TFE)</p>
24	2.0	3.3	
22	2.5	4.5	
20	3.7	6.5	
18	5.0	9.2	
16	6.5	13.0	
14	8.5	19.0	
12	11.5	25.0	
10	16.5	33.0	
8	23.0	44.0	

Reproduced from  
best available copy.



TABLE 17. DERATING OUTLINE OF QUARTZ CRYSTALS

Class	Derate To	Remarks
All Crystals	50% of rated drive level	



PC145S- 8000  
Amendment 1  
17 December 1971

FAIRCHILD INDUSTRIES, INC.  
FAIRCHILD REPUBLIC DIVISION  
New Product Development Section  
Farmingdale, New York 11735

PRODUCT SPECIFICATION FOR:  
SMS POWER CONDITIONER  
(AMENDMENT 1)

Prepared by: Robert Gelbman  
R. Gelbman

Approved by: William J. Guman  
W. J. Guman, Program Manager

PC145S8000  
Amendment 1  
17 December 1971

The following interpretations and clarifications of Fairchild Product Specification PC004S8000 -(PC145S8000), SMS Power Conditioner, are presented as Amendment 1.

Paragraph 3.3.1: The reference to two (2) 4.0 microfarad  $\pm 10\%$  capacitors is changed to read: two (2) 4.0 microfarad  $\pm 5\%$  capacitors. This change then agrees with the actual worst case tolerance of the capacitors that will be used. The charge time of  $500 \pm 20$  milliseconds is changed to read:  $500 \pm 40$  milliseconds. This change then agrees with the next sentence in the specification which says that the charge time shall not in any case exceed 540 milliseconds with  $29.4 \pm 0.2$  volts input.

Paragraph 3.3.2: This paragraph will be interpreted as meaning that the two (2) 1.0 microfarad  $\pm 5\%$  capacitors connected in parallel shall be charged to  $620 \pm 20$  volts D.C. in a charge time not to exceed 540 milliseconds.

Paragraph 3.3.5: Wilmore Electronics will plan for the 29.4-volt output which is supplied to the control logic to have a current capability of 25 milliamperes.

Paragraph 3.6.2: The following items will fulfill the Wilmore documentation requirements of 3.6.2 (a):

1. Complete Electrical Schematic and Parts List
2. Detailed Envelope Drawing defining outside dimensions, mounting arrangements, connector locations, etc.
3. Printed Circuit Board Layout Sheets showing the physical location of each electronic component and keying the component identifications to the schematic and parts list.
4. Telemetry calibration curves/data
5. Electrical test data (actually this is also covered in 3.6.2(e)).

Paragraph 3.3.7: Fairchild Industries will provide the thermister to measure items 3.3.7d mean internal thruster temperature.

Paragraph 3.5.17: Conducted and radiated EMI measurements shall be performed by Fairchild Industries.



C-2.1

FOLDOUT FRAME

Hand-drawn technical drawing of a mechanical assembly. The drawing shows a cross-section of a component with various dimensions and features. Key dimensions include: .09, .170, .34, .25, .2700, .060R, .010R (TYP), .631, .630, 0, .431, .430, .470, .343, .060R (TYP), 0, .274 (TYP), and .375. A note at the top left indicates: "DO NOT DEBURR C/S TO FASTENER PRESS FIT". The drawing is labeled with "215" and "215" near the top, and "215" near the bottom right.




Figure 11. Bulkhead Assembly, Enclosure

[illegible]

PART NUMBER MARKING PER MIL-STD-130										LIST OF MATERIAL										UNLESS OTHERWISE SPECIFIED, ALL MATERIALS ARE TO BE OF THE HIGHEST QUALITY AVAILABLE AND TO BE OF THE HIGHEST GRADE AVAILABLE.									
										1. QUANTITY 2. PART NUMBER 3. DESCRIPTION 4. QUANTITY 5. PART NUMBER 6. DESCRIPTION 7. QUANTITY 8. PART NUMBER 9. DESCRIPTION 10. QUANTITY 11. PART NUMBER 12. DESCRIPTION 13. QUANTITY 14. PART NUMBER 15. DESCRIPTION 16. QUANTITY 17. PART NUMBER 18. DESCRIPTION 19. QUANTITY 20. PART NUMBER 21. DESCRIPTION 22. QUANTITY 23. PART NUMBER 24. DESCRIPTION 25. QUANTITY 26. PART NUMBER 27. DESCRIPTION 28. QUANTITY 29. PART NUMBER 30. DESCRIPTION 31. QUANTITY 32. PART NUMBER 33. DESCRIPTION 34. QUANTITY 35. PART NUMBER 36. DESCRIPTION 37. QUANTITY 38. PART NUMBER 39. DESCRIPTION 40. QUANTITY 41. PART NUMBER 42. DESCRIPTION 43. QUANTITY 44. PART NUMBER 45. DESCRIPTION 46. QUANTITY 47. PART NUMBER 48. DESCRIPTION 49. QUANTITY 50. PART NUMBER 51. DESCRIPTION 52. QUANTITY 53. PART NUMBER 54. DESCRIPTION 55. QUANTITY 56. PART NUMBER 57. DESCRIPTION 58. QUANTITY 59. PART NUMBER 60. DESCRIPTION 61. QUANTITY 62. PART NUMBER 63. DESCRIPTION 64. QUANTITY 65. PART NUMBER 66. DESCRIPTION 67. QUANTITY 68. PART NUMBER 69. DESCRIPTION 70. QUANTITY 71. PART NUMBER 72. DESCRIPTION 73. QUANTITY 74. PART NUMBER 75. DESCRIPTION 76. QUANTITY 77. PART NUMBER 78. DESCRIPTION 79. QUANTITY 80. PART NUMBER 81. DESCRIPTION 82. QUANTITY 83. PART NUMBER 84. DESCRIPTION 85. QUANTITY 86. PART NUMBER 87. DESCRIPTION 88. QUANTITY 89. PART NUMBER 90. DESCRIPTION 91. QUANTITY 92. PART NUMBER 93. DESCRIPTION 94. QUANTITY 95. PART NUMBER 96. DESCRIPTION 97. QUANTITY 98. PART NUMBER 99. DESCRIPTION 100. QUANTITY 101. PART NUMBER 102. DESCRIPTION 103. QUANTITY 104. PART NUMBER 105. DESCRIPTION 106. QUANTITY 107. PART NUMBER 108. DESCRIPTION 109. QUANTITY 110. PART NUMBER 111. DESCRIPTION 112. QUANTITY 113. PART NUMBER 114. DESCRIPTION 115. QUANTITY 116. PART NUMBER 117. DESCRIPTION 118. QUANTITY 119. PART NUMBER 120. DESCRIPTION 121. QUANTITY 122. PART NUMBER 123. DESCRIPTION 124. QUANTITY 125. PART NUMBER 126. DESCRIPTION 127. QUANTITY 128. PART NUMBER 129. DESCRIPTION 130. QUANTITY 131. PART NUMBER 132. DESCRIPTION 133. QUANTITY 134. PART NUMBER 135. DESCRIPTION 136. QUANTITY 137. PART NUMBER 138. DESCRIPTION 139. QUANTITY 140. PART NUMBER 141. DESCRIPTION 142. QUANTITY 143. PART NUMBER 144. DESCRIPTION 145. QUANTITY 146. PART NUMBER 147. DESCRIPTION 148. QUANTITY 149. PART NUMBER 150. DESCRIPTION 151. QUANTITY 152. PART NUMBER 153. DESCRIPTION 154. QUANTITY 155. PART NUMBER 156. DESCRIPTION 157. QUANTITY 158. PART NUMBER 159. DESCRIPTION 160. QUANTITY 161. PART NUMBER 162. DESCRIPTION 163. QUANTITY 164. PART NUMBER 165. DESCRIPTION 166. QUANTITY 167. PART NUMBER 168. DESCRIPTION 169. QUANTITY 170. PART NUMBER 171. DESCRIPTION 172. QUANTITY 173. PART NUMBER 174. DESCRIPTION 175. QUANTITY 176. PART NUMBER 177. DESCRIPTION 178. QUANTITY 179. PART NUMBER 180. DESCRIPTION 181. QUANTITY 182. PART NUMBER 183. DESCRIPTION 184. QUANTITY 185. PART NUMBER 186. DESCRIPTION 187. QUANTITY 188. PART NUMBER 189. DESCRIPTION 190. QUANTITY 191. PART NUMBER 192. DESCRIPTION 193. QUANTITY 194. PART NUMBER 195. DESCRIPTION 196. QUANTITY 197. PART NUMBER 198. DESCRIPTION 199. QUANTITY 200. PART NUMBER 201. DESCRIPTION 202. QUANTITY 203. PART NUMBER 204. DESCRIPTION 205. QUANTITY 206. PART NUMBER 207. DESCRIPTION 208. QUANTITY 209. PART NUMBER 210. DESCRIPTION 211. QUANTITY 212. PART NUMBER 213. DESCRIPTION 214. QUANTITY 215. PART NUMBER 216. DESCRIPTION 217. QUANTITY 218. PART NUMBER 219. DESCRIPTION 220. QUANTITY 221. PART NUMBER 222. DESCRIPTION 223. QUANTITY 224. PART NUMBER 225. DESCRIPTION 226. QUANTITY 227. PART NUMBER 228. DESCRIPTION 229. QUANTITY 230. PART NUMBER 231. DESCRIPTION 232. QUANTITY 233. PART NUMBER 234. DESCRIPTION 235. QUANTITY 236. PART NUMBER 237. DESCRIPTION 238. QUANTITY 239. PART NUMBER 240. DESCRIPTION 241. QUANTITY 242. PART NUMBER 243. DESCRIPTION 244. QUANTITY 245. PART NUMBER 246. DESCRIPTION 247. QUANTITY 248. PART NUMBER 249. DESCRIPTION 250. QUANTITY 251. PART NUMBER 252. DESCRIPTION 253. QUANTITY 254. PART NUMBER 255. DESCRIPTION 256. QUANTITY 257. PART NUMBER 258. DESCRIPTION 259. QUANTITY 260. PART NUMBER 261. DESCRIPTION 262. QUANTITY 263. PART NUMBER 264. DESCRIPTION 265. QUANTITY 266. PART NUMBER 267. DESCRIPTION 268. QUANTITY 269. PART NUMBER 270. DESCRIPTION 271. QUANTITY 272. PART NUMBER 273. DESCRIPTION 274. QUANTITY 275. PART NUMBER 276. DESCRIPTION 277. QUANTITY 278. PART NUMBER 279. DESCRIPTION 280. QUANTITY 281. PART NUMBER 282. DESCRIPTION 283. QUANTITY 284. PART NUMBER 285. DESCRIPTION 286. QUANTITY 287. PART NUMBER 288. DESCRIPTION 289. QUANTITY 290. PART NUMBER 291. DESCRIPTION 292. QUANTITY 293. PART NUMBER 294. DESCRIPTION 295. QUANTITY 296. PART NUMBER 297. DESCRIPTION 298. QUANTITY 299. PART NUMBER 300. DESCRIPTION 301. QUANTITY 302. PART NUMBER 303. DESCRIPTION 304. QUANTITY 305. PART NUMBER 306. DESCRIPTION 307. QUANTITY 308. PART NUMBER 309. DESCRIPTION 310. QUANTITY 311. PART NUMBER 312. DESCRIPTION 313. QUANTITY 314. PART NUMBER 315. DESCRIPTION 316. QUANTITY 317. PART NUMBER 318. DESCRIPTION 319. QUANTITY 320. PART NUMBER 321. DESCRIPTION 322. QUANTITY 323. PART NUMBER 324. DESCRIPTION 325. QUANTITY 326. PART NUMBER 327. DESCRIPTION 328. QUANTITY 329. PART NUMBER 330. DESCRIPTION 331. QUANTITY 332. PART NUMBER 333. DESCRIPTION 334. QUANTITY 335. PART NUMBER 336. DESCRIPTION 337. QUANTITY 338. PART NUMBER 339. DESCRIPTION 340. QUANTITY 341. PART NUMBER 342. DESCRIPTION 343. QUANTITY 344. PART NUMBER 345. DESCRIPTION 346. QUANTITY 347. PART NUMBER 348. DESCRIPTION 349. QUANTITY 350. PART NUMBER 351. DESCRIPTION 352. QUANTITY 353. PART NUMBER 354. DESCRIPTION 355. QUANTITY 356. PART NUMBER 357. DESCRIPTION 358. QUANTITY 359. PART NUMBER 360. DESCRIPTION 361. QUANTITY 362. PART NUMBER 363. DESCRIPTION 364. QUANTITY 365. PART NUMBER 366. DESCRIPTION 367. QUANTITY 368. PART NUMBER 369. DESCRIPTION 370. QUANTITY 371. PART NUMBER 372. DESCRIPTION 373. QUANTITY 374. PART NUMBER 375. DESCRIPTION 376. QUANTITY 377. PART NUMBER 378. DESCRIPTION 379. QUANTITY 380. PART NUMBER 381. DESCRIPTION 382. QUANTITY 383. PART NUMBER 384. DESCRIPTION 385. QUANTITY 386. PART NUMBER 387. DESCRIPTION 388. QUANTITY 389. PART NUMBER 390. DESCRIPTION 391. QUANTITY 392. PART NUMBER 393. DESCRIPTION 394. QUANTITY 395. PART NUMBER 396. DESCRIPTION 397. QUANTITY 398. PART NUMBER 399. DESCRIPTION 400. QUANTITY 401. PART NUMBER 402. DESCRIPTION 403. QUANTITY 404. PART NUMBER 405. DESCRIPTION 406. QUANTITY 407. PART NUMBER 408. DESCRIPTION 409. QUANTITY 410. PART NUMBER 411. DESCRIPTION 412. QUANTITY 413. PART NUMBER 414. DESCRIPTION 415. QUANTITY 416. PART NUMBER 417. DESCRIPTION 418. QUANTITY 419. PART NUMBER 420. DESCRIPTION 421. QUANTITY 422. PART NUMBER 423. DESCRIPTION 424. QUANTITY 425. PART NUMBER 426. DESCRIPTION 427. QUANTITY 428. PART NUMBER 429. DESCRIPTION 430. QUANTITY 431. PART NUMBER 432. DESCRIPTION 433. QUANTITY 434. PART NUMBER 435. DESCRIPTION 436. QUANTITY 437. PART NUMBER 438. DESCRIPTION 439. QUANTITY 440. PART NUMBER 441. DESCRIPTION 442. QUANTITY 443. PART NUMBER 444. DESCRIPTION 445. QUANTITY 446. PART NUMBER 447. DESCRIPTION 448. QUANTITY 449. PART NUMBER 450. DESCRIPTION 451. QUANTITY 452. PART NUMBER 453. DESCRIPTION 454. QUANTITY 455. PART NUMBER 456. DESCRIPTION 457. QUANTITY 458. PART NUMBER 459. DESCRIPTION 460. QUANTITY 461. PART NUMBER 462. DESCRIPTION 463. QUANTITY 464. PART NUMBER 465. DESCRIPTION 466. QUANTITY 467. PART NUMBER 468. DESCRIPTION 469. QUANTITY 470. PART NUMBER 471. DESCRIPTION 472. QUANTITY 473. PART NUMBER 474. DESCRIPTION 475. QUANTITY 476. PART NUMBER 477. DESCRIPTION 478. QUANTITY 479. PART NUMBER 480. DESCRIPTION 481. QUANTITY 482. PART NUMBER 483. DESCRIPTION 484. QUANTITY 485. PART NUMBER 486. DESCRIPTION 487. QUANTITY 488. PART NUMBER 489. DESCRIPTION 490. QUANTITY 491. PART NUMBER 492. DESCRIPTION 493. QUANTITY 494. PART NUMBER 495. DESCRIPTION 496. QUANTITY 497. PART NUMBER 498. DESCRIPTION 499. QUANTITY 500. PART NUMBER 501. DESCRIPTION 502. QUANTITY 503. PART NUMBER 504. DESCRIPTION 505. QUANTITY 506. PART NUMBER 507. DESCRIPTION 508. QUANTITY 509. PART NUMBER 510. DESCRIPTION 511. QUANTITY 512. PART NUMBER 513. DESCRIPTION 514. QUANTITY 515. PART NUMBER 516. DESCRIPTION 517. QUANTITY 518. PART NUMBER 519. DESCRIPTION 520. QUANTITY 521. PART NUMBER 522. DESCRIPTION 523. QUANTITY 524. PART NUMBER 525. DESCRIPTION 526. QUANTITY 527. PART NUMBER 528. DESCRIPTION 529. QUANTITY 530. PART NUMBER 531. DESCRIPTION 532. QUANTITY 533. PART NUMBER 534. DESCRIPTION 535. QUANTITY 536. PART NUMBER 537. DESCRIPTION 538. QUANTITY 539. PART NUMBER 540. DESCRIPTION 541. QUANTITY 542. PART NUMBER 543. DESCRIPTION 544. QUANTITY 545. PART NUMBER 546. DESCRIPTION 547. QUANTITY 548. PART NUMBER 549. DESCRIPTION 550. QUANTITY 551. PART NUMBER 552. DESCRIPTION 553. QUANTITY 554. PART NUMBER 555. DESCRIPTION 556. QUANTITY 557. PART NUMBER 558. DESCRIPTION 559. QUANTITY 560. PART NUMBER 561. DESCRIPTION 562. QUANTITY 563. PART NUMBER 564. DESCRIPTION 565. QUANTITY 566. PART NUMBER 567. DESCRIPTION 568. QUANTITY 569. PART NUMBER 570. DESCRIPTION 571. QUANTITY 572. PART NUMBER 573. DESCRIPTION 574. QUANTITY 575. PART NUMBER 576. DESCRIPTION 577. QUANTITY 578. PART NUMBER 579. DESCRIPTION 580. QUANTITY 581. PART NUMBER 582. DESCRIPTION 583. QUANTITY 584. PART NUMBER 585. DESCRIPTION 586. QUANTITY 587. PART NUMBER 588. DESCRIPTION 589. QUANTITY 590. PART NUMBER 591. DESCRIPTION 592. QUANTITY 593. PART NUMBER 594. DESCRIPTION 595. QUANTITY 596. PART NUMBER 597. DESCRIPTION 598. QUANTITY 599. PART NUMBER 600. DESCRIPTION 601. QUANTITY 602. PART NUMBER 603. DESCRIPTION 604. QUANTITY 605. PART NUMBER 606. DESCRIPTION 607. QUANTITY 608. PART NUMBER 609. DESCRIPTION 610. QUANTITY 611. PART NUMBER 612. DESCRIPTION 613. QUANTITY 614. PART NUMBER 615. DESCRIPTION 616. QUANTITY 617. PART NUMBER 618. DESCRIPTION 619. QUANTITY 620. PART NUMBER 621. DESCRIPTION 622. QUANTITY 623. PART NUMBER 624. DESCRIPTION 625. QUANTITY 626. PART NUMBER 627. DESCRIPTION 628. QUANTITY 629. PART NUMBER 630. DESCRIPTION 631. QUANTITY 632. PART NUMBER 633. DESCRIPTION 634. QUANTITY 635. PART NUMBER 636. DESCRIPTION 637. QUANTITY 638. PART NUMBER 639. DESCRIPTION 640. QUANTITY 641. PART NUMBER 642. DESCRIPTION 643. QUANTITY 644. PART NUMBER 645. DESCRIPTION 646. QUANTITY 647. PART NUMBER 648. DESCRIPTION 649. QUANTITY 650. PART NUMBER 651. DESCRIPTION 652. QUANTITY 653. PART NUMBER 654. DESCRIPTION 655. QUANTITY 656. PART NUMBER 657. DESCRIPTION 658. QUANTITY 659. PART NUMBER 660. DESCRIPTION 661. QUANTITY 662. PART NUMBER 663. DESCRIPTION 664. QUANTITY 665. PART NUMBER 666. DESCRIPTION 667. QUANTITY 668. PART NUMBER 669. DESCRIPTION 670. QUANTITY 671. PART NUMBER 672. DESCRIPTION 673. QUANTITY 674. PART NUMBER 675. DESCRIPTION 676. QUANTITY 677. PART NUMBER 678. DESCRIPTION 679. QUANTITY 680. PART NUMBER 681. DESCRIPTION 682. QUANTITY 683. PART NUMBER 684. DESCRIPTION 685. QUANTITY 686. PART NUMBER 687. DESCRIPTION 688. QUANTITY 689. PART NUMBER 690. DESCRIPTION 691. QUANTITY 692. PART NUMBER 693. DESCRIPTION 694. QUANTITY 695. PART NUMBER 696. DESCRIPTION 697. QUANTITY 698. PART NUMBER 699. DESCRIPTION 700. QUANTITY 701. PART NUMBER 702. DESCRIPTION 703. QUANTITY 704. PART NUMBER 705. DESCRIPTION 706. QUANTITY 707. PART NUMBER 708. DESCRIPTION 709. QUANTITY 710. PART NUMBER 711. DESCRIPTION 712. QUANTITY 713. PART NUMBER 714. DESCRIPTION 715. QUANTITY 716. PART NUMBER 717. DESCRIPTION 718. QUANTITY 719. PART NUMBER 720. DESCRIPTION 721. QUANTITY 722. PART NUMBER 723. DESCRIPTION 724. QUANTITY 725. PART NUMBER 726. DESCRIPTION 727. QUANTITY 728. PART NUMBER 729. DESCRIPTION 730. QUANTITY 731. PART NUMBER 732. DESCRIPTION 733. QUANTITY 734. PART NUMBER 735. DESCRIPTION 736. QUANTITY 737. PART NUMBER 738. DESCRIPTION 739. QUANTITY 740. PART NUMBER 741. DESCRIPTION 742. QUANTITY 743. PART NUMBER 744. DESCRIPTION 745. QUANTITY 746. PART NUMBER 747. DESCRIPTION 748. QUANTITY 749. PART NUMBER 750. DESCRIPTION 751. QUANTITY 752. PART NUMBER 753. DESCRIPTION 754. QUANTITY 755. PART NUMBER 756. DESCRIPTION 757. QUANTITY 758. PART NUMBER 759. DESCRIPTION 760. QUANTITY 761. PART NUMBER 762. DESCRIPTION 763. QUANTITY 764. PART NUMBER 765. DESCRIPTION 766. QUANTITY 767. PART NUMBER 768. DESCRIPTION 769. QUANTITY 770. PART NUMBER 771. DESCRIPTION 772. QUANTITY 773. PART NUMBER 774. DESCRIPTION 775. QUANTITY 776. PART NUMBER 777. DESCRIPTION 778. QUANTITY 779. PART NUMBER 780. DESCRIPTION 781. QUANTITY 782. PART NUMBER 783. DESCRIPTION 784. QUANTITY 785. PART NUMBER 786. DESCRIPTION 787. QUANTITY 788. PART NUMBER 789. DESCRIPTION 790. QUANTITY 791. PART NUMBER 792. DESCRIPTION 793. QUANTITY 794. PART NUMBER 795. DESCRIPTION 796. QUANTITY 797. PART NUMBER 798. DESCRIPTION 799. QUANTITY 800. PART NUMBER 801. DESCRIPTION 802. QUANTITY 803. PART NUMBER 804. DESCRIPTION 805. QUANTITY 806. PART NUMBER 807. DESCRIPTION 808. QUANTITY 809. PART NUMBER 810. DESCRIPTION 811. QUANTITY 812. PART NUMBER 813. DESCRIPTION 814. QUANTITY 815. PART NUMBER 816. DESCRIPTION 817. QUANTITY 818. PART NUMBER 819. DESCRIPTION 820. QUANTITY 821. PART NUMBER 822. DESCRIPTION 823. QUANTITY 824. PART NUMBER 825. DESCRIPTION 826. QUANTITY 827. PART NUMBER 828. DESCRIPTION 829. QUANTITY 830. PART NUMBER 831. DESCRIPTION 832. QUANTITY 833. PART NUMBER 834. DESCRIPTION 835. QUANTITY 836. PART NUMBER 837. DESCRIPTION 838. QUANTITY 839. PART NUMBER 840. DESCRIPTION 841. QUANTITY 842. PART NUMBER 843. DESCRIPTION 844. QUANTITY 845. PART NUMBER 846. DESCRIPTION 847. QUANTITY 848. PART NUMBER 849. DESCRIPTION 850. QUANTITY 851. PART NUMBER 852. DESCRIPTION 853. QUANTITY 854. PART NUMBER 855. DESCRIPTION 856. QUANTITY 857. PART NUMBER 858. DESCRIPTION 859. QUANTITY 860. PART NUMBER 861. DESCRIPTION 862. QUANTITY 863. PART NUMBER 864. DESCRIPTION 865. QUANTITY 866. PART NUMBER 867. DESCRIPTION 868. QUANTITY 869. PART NUMBER 870. DESCRIPTION 871. QUANTITY 872. PART NUMBER 873. DESCRIPTION 874. QUANTITY 875. PART NUMBER 876. DESCRIPTION 877. QUANTITY 878. PART NUMBER 879. DESCRIPTION 880. QUANTITY 881. PART NUMBER 882. DESCRIPTION 883. QUANTITY 884. PART NUMBER 885. DESCRIPTION 886. QUANTITY 887. PART NUMBER 888. DESCRIPTION 889. QUANTITY 890. PART NUMBER 891. DESCRIPTION 892. QUANTITY 893. PART NUMBER 894. DESCRIPTION 895. QUANTITY 896. PART NUMBER 897. DESCRIPTION 898. QUANTITY 899. PART NUMBER 900. DESCRIPTION 901. QUANTITY 902. PART NUMBER 903. DESCRIPTION 904. QUANTITY 905. PART NUMBER 906. DESCRIPTION 907. QUANTITY 908. PART NUMBER 909. DESCRIPTION 910. QUANTITY 911. PART NUMBER 912. DESCRIPTION 913. QUANTITY 914. PART NUMBER 915. DESCRIPTION 916. QUANTITY 917. PART NUMBER 918. DESCRIPTION 919. QUANTITY 920. PART NUMBER 921. DESCRIPTION 922. QUANTITY 923. PART NUMBER 924. DESCRIPTION 925. QUANTITY 926. PART NUMBER 927. DESCRIPTION 928. QUANTITY 929. PART NUMBER 930. DESCRIPTION 931. QUANTITY 932. PART NUMBER 933. DESCRIPTION 934. QUANTITY 935. PART NUMBER 936. DESCRIPTION 937. QUANTITY 938. PART NUMBER 939. DESCRIPTION 940. QUANTITY 941. PART NUMBER 942. DESCRIPTION 943. QUANTITY 944. PART NUMBER 945. DESCRIPTION 946. QUANTITY 947. PART NUMBER 948. DESCRIPTION 949. QUANTITY 950. PART NUMBER 951. DESCRIPTION 952. QUANTITY 953. PART NUMBER 954. DESCRIPTION 955. QUANTITY 956. PART NUMBER 957. DESCRIPTION 958. QUANTITY 959. PART NUMBER 960. DESCRIPTION 961. QUANTITY 962. PART NUMBER 963. DESCRIPTION 964. QUANTITY 965. PART NUMBER 966. DESCRIPTION 967. QUANTITY 968. PART NUMBER 969. DESCRIPTION 970. QUANTITY 971. PART NUMBER 972. DESCRIPTION 973. QUANTITY 974. PART NUMBER 975. DESCRIPTION 976. QUANTITY 977. PART NUMBER 978. DESCRIPTION 979. QUANTITY 980. PART NUMBER 981. DESCRIPTION 982. QUANTITY 983. PART NUMBER 984. DESCRIPTION 985. QUANTITY 986. PART NUMBER 987. DESCRIPTION 988. QUANTITY 989. PART NUMBER 990. DESCRIPTION 991. QUANTITY 992. PART NUMBER 993. DESCRIPTION 994. QUANTITY 995. PART NUMBER 996. DESCRIPTION 997. QUANTITY 998. PART NUMBER 999. DESCRIPTION 1000. QUANTITY 1001. PART NUMBER 1002. DESCRIPTION 1003. QUANTITY 1004. PART NUMBER 1005. DESCRIPTION 1006. QUANTITY 1007. PART NUMBER 1008. DESCRIPTION 1009. QUANTITY 1010. PART NUMBER 1011. DESCRIPTION 1012. QUANTITY 1013. PART NUMBER 1014. DESCRIPTION 1015. QUANTITY 1016. PART NUMBER 1017. DESCRIPTION 1018. QUANTITY 1019. PART NUMBER 1020. DESCRIPTION 1021. QUANTITY 1022. PART NUMBER 1023. DESCRIPTION 1024. QUANTITY 1025. PART NUMBER 1026. DESCRIPTION 1027. QUANTITY 1028. PART NUMBER 1029. DESCRIPTION 1030. QUANTITY 1031. PART NUMBER 1032. DESCRIPTION 1033. QUANTITY 1034. PART NUMBER 1035. DESCRIPTION 1036. QUANTITY 1037. PART NUMBER 1038. DESCRIPTION 1039. QUANTITY 1040. PART NUMBER 1041. DESCRIPTION 1042. QUANTITY 1043. PART NUMBER 1044. DESCRIPTION 1045. QUANTITY 1046. PART NUMBER 1047. DESCRIPTION 1048. QUANTITY 1049. PART NUMBER 1050. DESCRIPTION 1051. QUANTITY 1052. PART NUMBER 1053. DESCRIPTION 1054. QUANTITY 1055. PART NUMBER 1056. DESCRIPTION 1057. QUANTITY 1058. PART NUMBER 1059. DESCRIPTION 1060. QUANTITY 1061. PART NUMBER 1062. DESCRIPTION 1063. QUANTITY 1064. PART NUMBER 1065. DESCRIPTION 1066. QUANTITY 1067. PART NUMBER 1068. DESCRIPTION 1069. QUANTITY 1070. PART NUMBER 1071. DESCRIPTION 1072. QUANTITY 1073. PART NUMBER 1074. DESCRIPTION 1075. QUANTITY 1076. PART NUMBER 1077. DESCRIPTION 1078. QUANTITY 1079. PART NUMBER 1080. DESCRIPTION 1081. QUANTITY 1082. PART NUMBER 1083. DESCRIPTION 1084. QUANTITY 1085. PART NUMBER 1086. DESCRIPTION 1087. QUANTITY 1088. PART NUMBER 1089. DESCRIPTION 1090. QUANTITY 1091. PART NUMBER 1092. DESCRIPTION 1093. QUANTITY 1094. PART NUMBER 1095. DESCRIPTION 1096. QUANTITY 1097. PART NUMBER 1098. DESCRIPTION 1099. QUANTITY 1100. PART NUMBER 1101. DESCRIPTION 1102. QUANTITY 1103. PART NUMBER 1104. DESCRIPTION 1105. QUANTITY 1106. PART NUMBER 1107. DESCRIPTION 1108. QUANTITY 1109. PART NUMBER 1110. DESCRIPTION 1111. QUANTITY 1112. PART NUMBER 1113. DESCRIPTION 1114. QUANTITY 1115. PART NUMBER 1116. DESCRIPTION 1117. QUANTITY 1118. PART NUMBER 1119. DESCRIPTION 1120. QUANTITY 1121. PART NUMBER 1122. DESCRIPTION 1123. QUANTITY 1124. PART NUMBER 1125. DESCRIPTION 1126. QUANTITY 1127. PART NUMBER 1128. DESCRIPTION 1129. QUANTITY 1130. PART NUMBER 1131. DESCRIPTION 1132. QUANTITY 1133. PART NUMBER 1134. DESCRIPTION 1135. QUANTITY 1136. PART NUMBER 1137. DESCRIPTION 1138. QUANTITY 1139. PART NUMBER 1140. DESCRIPTION 1141. QUANTITY 1142. PART NUMBER 1143. DESCRIPTION 1144. QUANTITY 1145. PART NUMBER 1146. DESCRIPTION 1147. QUANTITY 1148. PART NUMBER 1149. DESCRIPTION 1150. QUANTITY 1151. PART NUMBER 1152. DESCRIPTION 1153. QUANTITY 1154. PART NUMBER 1155. DESCRIPTION 1156. QUANTITY 1157. PART NUMBER 1158. DESCRIPTION 1159. QUANTITY 1160. PART NUMBER 1161. DESCRIPTION 1162. QUANTITY 1163. PART NUMBER 1164. DESCRIPTION 1165. QUANTITY 1166. PART NUMBER 1167. DESCRIPTION 1168. QUANTITY 1169. PART NUMBER 1170. DESCRIPTION 1171. QUANTITY 1172. PART NUMBER 1173. DESCRIPTION 1174. QUANTITY 1175. PART NUMBER 1176. DESCRIPTION 1177. QUANTITY 1178. PART NUMBER 1179. DESCRIPTION 1180. QUANTITY 1181. PART NUMBER 1182. DESCRIPTION 1183. QUANTITY 1184. PART NUMBER 1185. DESCRIPTION 1186. QUANTITY 1187. PART NUMBER 1188. DESCRIPTION 1189. QUANTITY 1190. PART NUMBER 1191. DESCRIPTION 1192. QUANTITY 1193. PART NUMBER 1194. DESCRIPTION 1195. QUANTITY 1196. PART NUMBER 1197. DESCRIPTION 1198. QUANTITY 1199. PART NUMBER 1200. DESCRIPTION 1201. QUANTITY 1202. PART NUMBER 1203. DESCRIPTION 1204. QUANTITY 1205. PART NUMBER 1206. DESCRIPTION 1207. QUANTITY 1208. PART NUMBER 1209. DESCRIPTION 1210. QUANTITY 1211. PART NUMBER 1212. DESCRIPTION 1213. QUANTITY 1214. PART NUMBER 1215. DESCRIPTION 1216. QUANTITY 1217. PART NUMBER 1218. DESCRIPTION 1219. QUANTITY 1220. PART NUMBER 1221. DESCRIPTION 1222. QUANTITY 1223. PART NUMBER 1224. DESCRIPTION 1225. QUANTITY 1226. PART NUMBER 1227. DESCRIPTION 1228. QUANTITY 1229. PART NUMBER 1230. DESCRIPTION 1231. QUANTITY 1232. PART NUMBER 1233. DESCRIPTION 1234. QUANTITY 1235. PART NUMBER 1236. DESCRIPTION 1237. QUANTITY 1238. PART NUMBER 1239. DESCRIPTION 1240. QUANTITY 1241. PART NUMBER 1242. DESCRIPTION 1243. QUANTITY 1244. PART NUMBER 1245. DESCRIPTION 1246. QUANTITY 1247. PART NUMBER 1248. DESCRIPTION 1249. QUANTITY 1250. PART NUMBER 1251. DESCRIPTION 1252. QUANTITY 1253. PART NUMBER 1254. DESCRIPTION 1255. QUANTITY 1256. PART NUMBER 1257. DESCRIPTION 1258. QUANTITY 1259. PART NUMBER 1260. DESCRIPTION 1261. QUANTITY 1262. PART NUMBER 1263. DESCRIPTION 1264. QUANTITY 1265. PART NUMBER 1266. DESCRIPTION 1267. QUANTITY 1268. PART NUMBER 1269. DESCRIPTION 1270. QUANTITY 1271. PART NUMBER 1272. DESCRIPTION 1273. QUANTITY 1274. PART NUMBER 1275. DESCRIPTION 1276. QUANTITY 1277. PART NUMBER 1278. DESCRIPTION 1279. QUANTITY 1280. PART NUMBER 1281. DESCRIPTION 1282. QUANTITY 1283. PART NUMBER 1284. DESCRIPTION 1285. QUANTITY 1286. PART NUMBER 1287. DESCRIPTION 1288. QUANTITY 1289. PART NUMBER 1290. DESCRIPTION 1291. QUANTITY 1292. PART NUMBER 1293. DESCRIPTION 1294. QUANTITY 1295. PART NUMBER 1296. DESCRIPTION 1297. QUANTITY 1298. PART NUMBER 1299. DESCRIPTION 1300. QUANTITY 1301. PART NUMBER 1302. DESCRIPTION 1303. QUANTITY 1304. PART NUMBER 1305. DESCRIPTION 1306. QUANTITY 1307. PART NUMBER 1308. DESCRIPTION 1309. QUANTITY 1310. PART NUMBER 1311. DESCRIPTION 1312. QUANTITY 1313. PART NUMBER 1314. DESCRIPTION 1315. QUANTITY 1316. PART NUMBER 1317. DESCRIPTION 1318. QUANTITY 1319. PART NUMBER 1320. DESCRIPTION 1321. QUANTITY 1322. PART NUMBER 1323. DESCRIPTION 1324. QUANTITY 1325. PART NUMBER 1326. DESCRIPTION 1327. QUANTITY 1328. PART NUMBER 1329. DESCRIPTION 1330. QUANTITY 1331. PART NUMBER 1332. DESCRIPTION 1333. QUANTITY 1334. PART NUMBER 1335. DESCRIPTION 1336. QUANTITY 1337. PART NUMBER 1338. DESCRIPTION 1339. QUANTITY 1340. PART NUMBER 1341. DESCRIPTION 1342. QUANTITY 1343. PART NUMBER 1344. DESCRIPTION 1345. QUANTITY 1346. PART NUMBER 1347. DESCRIPTION 1348. QUANTITY 1349. PART NUMBER 1350. DESCRIPTION 1351. QUANTITY 1352. PART NUMBER 1353. DESCRIPTION 1354. QUANTITY 1355. PART NUMBER 1356. DESCRIPTION 1357. QUANTITY 1358. PART NUMBER 1359. DESCRIPTION 1360. QUANTITY 1361. PART NUMBER 1362. DESCRIPTION 1363. QUANTITY 1364. PART NUMBER 1365. DESCRIPTION 1366. QUANTITY 1367. PART NUMBER 1368. DESCRIPTION 1369. QUANTITY 1370. PART NUMBER 1371. DESCRIPTION 1372. QUANTITY 1373. PART NUMBER 1374. DESCRIPTION 1375. QUANTITY 1376. PART NUMBER 1377. DESCRIPTION 1378. QUANTITY 1379. PART NUMBER 1380. DESCRIPTION 1381. QUANTITY 1382. PART NUMBER 1383. DESCRIPTION 1384. QUANTITY 1385. PART NUMBER 1386. DESCRIPTION 1387. QUANTITY 1388. PART NUMBER 1389. DESCRIPTION 1390. QUANTITY 1391. PART NUMBER 1392. DESCRIPTION 1393. QUANTITY 1394. PART NUMBER 1395. DESCRIPTION 1396. QUANTITY 1397. PART NUMBER 1398. DESCRIPTION 1399. QUANTITY 1400. PART NUMBER 1401. DESCRIPTION 1402. QUANTITY 1403. PART NUMBER 1404. DESCRIPTION 1405. QUANTITY 1406. PART NUMBER 1407. DESCRIPTION 1408. QUANTITY 1409. PART NUMBER 1410. DESCRIPTION 1411. QUANTITY 1412. PART NUMBER 1413. DESCRIPTION 1414. QUANTITY 1415. PART NUMBER 1416. DESCRIPTION 1417. QUANTITY 1418. PART NUMBER 1419. DESCRIPTION 1420. QUANTITY 1421. PART NUMBER 1422. DESCRIPTION 1423. QUANTITY 1424. PART NUMBER 1425. DESCRIPTION 1426. QUANTITY 1427. PART NUMBER 1428. DESCRIPTION 1429. QUANTITY 1430. PART NUMBER 1431. DESCRIPTION 1432. QUANTITY 1433. PART NUMBER 1434. DESCRIPTION 1435. QUANTITY 1436. PART NUMBER 1437. DESCRIPTION 1438. QUANTITY 1439. PART NUMBER 1440. DESCRIPTION 1441. QUANTITY 1442. PART NUMBER 1443. DESCRIPTION 1444. QUANTITY 1445. PART NUMBER 1446. DESCRIPTION 1447. QUANTITY 1448. PART NUMBER 1449. DESCRIPTION 1450. QUANTITY 1451. PART NUMBER 1452. DESCRIPTION 1453. QUANTITY 1454. PART NUMBER 1455. DESCRIPTION 1456. QUANTITY 1457. PART NUMBER 1458. DESCRIPTION 1459. QUANTITY 1460. PART NUMBER 1461. DESCRIPTION 1462. QUANTITY 1463. PART NUMBER 1464. DESCRIPTION 1465. QUANTITY 1466. PART NUMBER 1467. DESCRIPTION 1468. QUANTITY 1469. PART NUMBER 1470. DESCRIPTION 1471. QUANTITY 1472. PART NUMBER 1473. DESCRIPTION 1474. QUANTITY 1475. PART NUMBER 1476. DESCRIPTION 1477. QUANTITY 1478. PART NUMBER 1479. DESCRIPTION 1480. QUANTITY 1481. PART NUMBER 1482. DESCRIPTION 1483. QUANTITY 1484. PART NUMBER 1485. DESCRIPTION 1486. QUANTITY 1487. PART NUMBER 1488. DESCRIPTION 1489. QUANTITY 1490. PART NUMBER 1491. DESCRIPTION 1492. QUANTITY 1493. PART NUMBER 1494. DESCRIPTION 1495. QUANTITY 1496. PART NUMBER 1497. DESCRIPTION 1498. QUANTITY 1499. PART NUMBER 1500. DESCRIPTION 1501. QUANTITY 1502. PART NUMBER 1503. DESCRIPTION 1504. QUANTITY 1505. PART NUMBER 1506. DESCRIPTION 1507. QUANTITY 1508. PART NUMBER 1509. DESCRIPTION 1510. QUANTITY 1511. PART NUMBER 1512. DESCRIPTION 1513. QUANTITY 1514. PART NUMBER 1515. DESCRIPTION 1516. QUANTITY 1517. PART NUMBER 1518. DESCRIPTION 1519. QUANTITY 1520. PART NUMBER 1521. DESCRIPTION 1522. QUANTITY 1523. PART NUMBER 1524. DESCRIPTION 1525. QUANTITY 1526. PART NUMBER 1527. DESCRIPTION 1528. QUANTITY 1529. PART NUMBER 1530. DESCRIPTION 1531. QUANTITY 1532. PART NUMBER 1533. DESCRIPTION 1534. QUANTITY 1535. PART NUMBER 1536. DESCRIPTION 1537. QUANTITY 1538. PART NUMBER 1539. DESCRIPTION 1540. QUANTITY 1541. PART NUMBER 1542. DESCRIPTION 1543. QUANTITY 1544. PART NUMBER 1545. DESCRIPTION 1546. QU																			

Technical drawing of a cylindrical component, showing three views: front view, side view, and end view.

**Front View (Left):**

- Top circular face: .155 R 10 PLCS, .090 R TYP, 2.930 DIA BASIC, 2.933, 2.670, 1.602, .464, .760.
- Bottom circular face: .760, .116 DIA (REF), MIL-W-46132.
- Central rectangular area: 2.210, 1.220, 2.510, .655, .0932 (4), 4 SYM.
- Annotations: MASK THIS FACE, MASK THIS AREA ON FAR SIDE.

**Side View (Middle):**

- Features 5, 6, 7, 8 are labeled.
- Annotation: MASK 8 PLCS.

**End View (Right):**

- Position to match PC145D1015-1 8 HOLES.
- Feature 10: 20 PLCS.
- Dimension: 3.000.
- Annotation: MASK 1.00 DIA FAR SIDE.

**General Notes:**

- TAP DRILL THRU TAP 4-40 UNC-2B 10 PLCS TO MATCH PC145D1050-1 ALONG WITH (4) .116 DIA HOLES AT A

1. ELECTRON BEAM WELD PER MIL-W-46132
2. LIGHTLY SAND BLAST -1 ON ALL SURFACES NOT MASKED OFF.  
AFTER CLEANING, APPLY POLYURETHANE COATING TO ALL SAND  
BLASTED SURFACES

PART NUMBER MARKING PER MIL-STD-130				LIST OF MATERIAL				UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION.			
								LAYOUT BY		<b>FAIRCHILD HILLER</b> <b>FAIRCHILD REPUBLIC DIVISION</b> FARMINGDALE, NEW YORK 11735	
								DRAWN BY	J.C.HUNTS 4-5-72		
								CHECKED			
								ENGINEER			
								STRUCTURES		<u>CASE ASSEMBLY -</u> <u>CAPACITOR</u> <u>SMS MICROTHRUSTER</u>	
				WEIGHTS				APPROVED			
				TOTAL WEIGHTS							
				DASH NO.				CONTRACT NO.			
				WEIGHT				NAS-5-11494			
PC145D1005 SMS MICROTHRUSTER 1 OF 1				DO NOT SCALE DRAWING ALL DIMENSIONS ARE IN INCHES UNLESS OTHERWISE NOTED TOLERANCES UNLESS NOTED XX±.01 XXX±.005 ANG±							
NEXT ASSEMBLY		USED ON		NEXT ASSY		FINAL ASSY		SIZE		CODE IDENT NO.	
								D		77751	PC145D1020
APPLICATION				QUANTITY REQD				SCALE		SHEET 1 OF	





Figure 13. Collector Plate, Negative

C-6

C-9




FOLDOUT FRAME.



[illegible]

FOLDOUT FRAME

FOLDOUT FRAME



PART No	O.D.	I.D.	L
-1	.218 .217	.140 .132	.308
-8	.312	.257	.130



PART No	O.D.	I.D.	L	T
-3	.216	.113	.130	.025
-4	.216	.113	.060	.025

- REQUIREMENTS FOR MACHINED PARTS  
(UNLESS OTHERWISE SPECIFIED.)
- (A) MAX. RHR OF MACHINED SURFACES (EXCLUDING HOLES)  $\checkmark$  ALL OVER
  - (B) MAX. RHR OF HOLES  $\checkmark$
  - (C) ALL FILLETS  $\checkmark$  .015 R  $\checkmark$  .005
  - (D) ALL EDGES TO BE ROUNDED  $\checkmark$  .010 MAX. (WHEN ROUNDING IS NOT SPECIFIED ON DWG.)
  - (E) TOLERANCES TO APPLY AFTER WELDING, HEAT TREATING, OR PLATING OPERATIONS. INITIAL DIMENSIONS OF SURFACES TO BE CADMIUM PLATED. SHALL NOT BE LESS THAN THE MINIMUM INDICATED FINISHED DIMENSIONS.
  - (F) APPLY PART NUMBER & INSPECTOR'S STAMP PER STANDARD PROCEDURES FOR SMALL PARTS

REVISIONS				DATE	APPROVED
TYPE OF CHANGE	EAI INC	REWORK PERMIT YES NO	ZONE LTR		

- NOTES:
- PACKAGE TOGETHER -19 & -21 AS A MATCHED SET.  
" " -23 & -25 " " " "












Figure 15. Insulators



QUANTITY REQD	CODE IDENT	PART NO. OR IDENTIFYING NO.	NOMENCLATURE OR DESCRIPTION	ZONE	DIA	THICK	WTH	LENGTH	STOCK SIZE	MATERIAL / MATERIAL SPECIFICATION / CONDITION	VENDOR NAME AND ADDRESS	PROCESS SPECIFICATION LINE NUMBERS	FINISH CODE	MARK CODE	FIELD NOTES	TRACE CODE	LINE NO.
		-27	INSULATOR		.25	.2	1.1			EPOXY RESIN GLASS FABRIC LAMINATE	NEMA GRADE G-10 MIL-P-18177-GEE						13
		-25			.32	.4	1.1										12
		-23			.25	.4	1.1										11
		-21			.32	.4	1.1										10
		-19			.25	.4	1.1										9
		-9			.75		.4										8
		-8			.37		.2										7
		-7			.62		.2										6
		-6			.62		.7										5
		-5			.37		.5										4
		-4			.25		.1										3
		-3			.25		.2										2
		-2			.50		.09										1
		PC145D1026-1	INSULATOR		.25		.4			EPOXY RESIN GLASS FABRIC LAMINATE	NEMA GRADE G-10 MIL-P-18177-GEE						1

PART NUMBER MARKING PER MIL-STD-130				UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION			
PC145D1015	SMS MICROTHRUSTER	1 OF 19	2 OF 19	LAYOUT BY	J. CHUNG	5-15-72	FAIRCHILD HILLER FAIRCHILD REPUBLIC DIVISION FARMINGDALE, NEW YORK 11735
PC145D1054		2 OF 9	2 OF 9	DRAWN BY	J. CHUNG	5-15-72	
PC145D1060		2 OF 8	2 OF 8	CHECKED			
PC145D1035		2 OF 6	2 OF 6	ENGINEER			
PC145D1030		1 OF 5	1 OF 5	STRUCTURES			INSULATOR DETAILS-
PC145D1050		2 OF 3	2 OF 3	APPROVED			
PC145D1050		1 OF 4	1 OF 4	CONTRACT NO.	NAS-5-11494		
PC145D1005	SMS MICROTHRUSTER	3 OF 2	3 OF 2	DO NOT SCALE DRAWING	ALL DIMENSIONS ARE IN INCHES	UNLESS OTHERWISE NOTED.	
NEXT ASSEMBLY		USED ON	NEXT ASSY	FINAL ASSY	QUANTITY REQD	SCALE 2/1	SHEET 1 OF

C-12

C-13

FOLDOUT FRAME/

FOLDOUT FRAME 2





Figure 16. Electrode-Positive

QUANTITY REQD	SYM	VENDOR DATA PER	CODE IDENT	PART OR IDENTIFYING NO.	ZONE	NOMENCLATURE OR DESCRIPTION	DIA	THICK	WIDTH	LENGTH	MATERIAL	MATL SPECIFICATION	TS 1000 PSI	UNIT WT
				- 1		ELECTRODE	.375	1.5	1.8		17-7 PH STAINLESS STEEL	MIL-S-25043 COND A		
LIST OF MATERIAL														
PART NUMBER MARKING PER MIL-STD-130														
UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION.														
DIMENSIONS ARE IN INCHES							DRAWN		SIGNATURE		13/78			
UNLESS OTHERWISE NOTED							CHECKED				FAIRCHILD HILLER			
DEC TOL							SH MET. RAD		GR ENGR		REPUBLIC AVIATION DIVISION			
2 PLACE ±							BEND:		STRUCT		FARMINGDALE, LONG ISLAND, NEW YORK			
3 PLACE ±							COR:		WEIGHTS		ELECTRODE-POSITIVE			
ANGULAR ±							DEBURR ALL EDGES							
APPLICABLE SPECIFICATIONS														
FINISH:							PROJ ENGR							
HEAT TREAT:														
BEND RELIEF:														
FOR ADDL SPEC SEE NOTE														
PC145D1031														
NEXT ASSEMBLY							USED ON		NEXT ASSY		FINAL ASSY			
APPLICATION							QUANTITY REQD		DO NOT SCALE DRAWING		CONTRACT NO.		NA5-5-11494	
											SCALE 2/1		UNLESS OTHERWISE NOTED SHEET	

FOLDOUT FRAME

PC145D1033					REVISIONS				
	TYPE OF CHANGE	EAI INC	REWORK PERMIT YES NO	SYM	DESCRIPTION			DATE	APPROVED










1. LIGHTLY SANDBLAST BOTH SIDES OF -1 EXCEPT IN AREA 'A' (FAR SIDE)

Figure 17. Collector Plate-Positive

[illegible]

FOLDOUT FRAME



				8	-8	INSULATOR	.062	1.5	1.7	} MYKROY GRADE 1100 MOLECULAR DIELECTRICS, INC. CLIFTON, NEW JERSEY				
				7	-7		.062	1.5	1.6					
				6	-6		.070	1.35	0.8					
				5	-5		.050	0.8	1.5					
				4	-4		.093	1.80	1.6					
				3	-3		.093	2.00	1.6					
				2	-2		.125	.38	1.1					
				1		PC145D1034-1	INSULATOR	.125	.38	1.1				

QUANTITY REQD	SYM	VENDOR DATA PER	CODE IDENT	PART OR IDENTIFYING NO.	ZONE	NOMENCLATURE OR DESCRIPTION	DIA	THICK	WIDTH	LENGTH	STOCK SIZE	MATERIAL	MATL SPECIFICATION	TS 1000 PSI	WT
LIST OF MATERIAL															
PART NUMBER MARKING PER MIL-STD-130							UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION OF THIS CODE OR IN PART IS PROHIBITED DRAWING, DESIGN AND OTHER DISCLOSURES PROTECTED BY PATENT RIGHTS OF FAYRCHILD HILLER CORPORATION.								
						DIMENSIONS ARE IN INCHES	DRAWN		CHECKED		<div>FAYRCHILD HILLER REPUBLIC AVIATION DIVISION FARMINGDALE, N.Y. 11735 NEW YORK</div> <div>INSULATORS POSITIVE &amp; NEGATIVE ELECTRODE SMS MICROTHRUSTER</div>				
						UNLESS OTHERWISE NOTED			GR ENGR						
						DEC TOL	SH MET. RAD		STRUCT						
						2 PLACE ±	BEND:		WEIGHTS						
						3 PLACE ±	COR:								
						ANGULAR ±	DEBURRALLEDGES				PROJ ENGR				
						APPLICABLE SPECIFICATIONS	CONTRACT NO.								
						FINISH: NONE	N45-5-11494								
						HEAT TREAT:									
						BEND RELIEF:									
						FOR ADDL SPEC SEE NOTE									
PC145D1035		SMS MICROTHRUSTER			2 OF 2										
PC145D1031		SMS MICROTHRUSTER			1 OF 3547										
PC145D1031		SMS MICROTHRUSTER			2 OF 146										
NEXT ASSEMBLY		USED ON		NEXT ASSY		FINAL ASSY						SIZE CODE IDENT NO		REV.	
												D 77751		PC145D1034	
APPLICATION						QUANTITY REQD						DO NOT SCALE DRAWING			
												SCALE: TWICE			
												SHEET			

FOLDOUT FRAME

1 FOLDOUT FRAME 2

PC145D1036										REVISIONS		DATE		APPROVED	
TYPE OF CHANGE										DESCRIPTION					
EAI INC										REWORK PERMIT		SYM			
										YES NO					

REQUIREMENTS FOR MACHINED PARTS  
UNLESS OTHERWISE SPECIFIED:

- (A) MAX. RHR OF MACHINED SURFACES (EXCLUDING HOLES)  $\sqrt{63}$  ALL OVER
- (B) MAX. RHR OF HOLES  $\sqrt{32}$
- (C) ALL FILLETS .060 R ± .010
- (D) ALL EDGES TO BE ROUNDED .010 MAX. (WHEN ROUNDING IS NOT SPECIFIED ON DWG.)
- (E) TOLERANCES TO APPLY AFTER WELDING, HEAT TREATING, OR PLATING OPERATIONS. INITIAL DIMENSIONS OF SURFACES TO BE CADMIUM PLATED, SHALL NOT BE LESS THAN THE MINIMUM INDICATED FINISHED DIMENSIONS.
- (F) APPLY PART NUMBER & INSPECTOR'S STAMP

Figure 19. Electrode Negative

QUANTITY REQD	SYM	VENOR DATA PER	CODE IDENT	PART OR IDENTIFYING NO.	ZONE	NOMENCLATURE OR DESCRIPTION	DIA	THICK	WIDTH	LENGTH	STOCK SIZE	MATERIAL	MATL SPECIFICATION	TS	UNIT
				PC145D1036-1		ELECTRODE	.375	1.5	2.0			17-7 PH STAINLESS STEEL	MIL-S-25043, COND A		WT

PART NUMBER MARKING PER MIL-STD-130										UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION.									
										FAIRCHILD HILLER REPUBLIC AVIATION DIVISION FARMINGDALE, LONG ISLAND, NEW YORK									
										ELECTRODE - NEGATIVE SMS MICROTHRUSTER									
										SIZE CODE IDENT NO. C 77751 PC145D1036									
										SCALE 2/1 UNLESS OTHERWISE NOTED SHEET									

APPLICATION				QUANTITY REQD				DO NOT SCALE DRAWING			
PC145D1035				SMS MICROTHRUSTER				1 OF 1			
NEXT ASSEMBLY				USED ON				NEXT ASSY FINAL ASSY			

FORM RAD 141

C-20

FOLD OUT FRAME 1

FOLD OUT FRAME 2

PC145D1037


TYPE OF CHANGE	EAI INC	REWORK PERM IT	SYM

REVISIONS

DESCRIPTION

DATE

APPROVED

REQUIREMENTS FOR MACHINED PARTS  
(UNLESS OTHERWISE SPECIFIED)


- (A) MAX. RHR OF MACHINED SURFACES (EXCLUDING HOLES)  $\frac{32}{\text{ALL OVER}}$
- (B) MAX. RHR OF HOLES  $\frac{32}{\text{ALL OVER}}$
- (C) ALL FILLETS  $.010 \text{ R} \pm .005$
- (D) ALL EDGES TO BE ROUNDED  $.010 \text{ MAX.}$  (WHEN ROUNDED IS NOT SPECIFIED ON DWG.)
- (E) TOLERANCES TO APPLY AFTER WELDING, HEAT TREATING, OR PLATING OPERATIONS. INITIAL DIMENSIONS OF SURFACES TO BE CADMIUM PLATED, SHALL NOT BE LESS THAN THE MINIMUM INDICATED FINISHED DIMENSIONS.
- (F) APPLY PART NUMBER & INSPECTOR'S STAMP PER STD PROCEDURES FOR SMALL PARTS.

1 SHOWN  
2 OPPOSITE

Figure 20. Insulator, Mykroy Sides

QUANTITY REQD	SYM	VENDOR DATA PER	CODE IDENT	PART OR IDENTIFYING NO.	ZONE	NOMENCLATURE OR DESCRIPTION	DIA	THICK	WIDTH	LENGTH	MATERIAL	MATL SPECIFICATION	TS 1000 PSI	UNIT WT
2					-2	INSULATOR	250	.8	1.8		MYKROY GRADE 1100			
1				PC145D1037-1		INSULATOR	250	.8	1.8		MOLECULAR DIELECTRICS INC., CLIFTON, N.J.			
LIST OF MATERIAL														
PART NUMBER MARKING PER MIL-STD-130														
UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION.														
FAIRCHILD HILLER REPUBLIC AVIATION DIVISION FARMINGDALE, LONG ISLAND, NEW YORK														
INSULATOR-FUEL SMS-MICROTHRUSTER														
SIZE CODE IDENT NO. REV.														
C 77751 PC145D1037														
SCALE TWICE UNLESS OTHERWISE NOTED SHEET														
CONTRACT NO. NIS-5-11494														
DO NOT SCALE DRAWING														
APPLICATION														
NEXT ASSEMBLY USED ON NEXT ASSY FINAL ASSY														
QUANTITY REQD														

FOLDOUT FRAME: 1



- \* 1. MATERIAL REQD FOR SOUND WELD AT SEAM; TO BE MACHINED OFF AFTER WELDING.
2. ELECTRON BEAM WELD PER MIL-W-46132

		46384	CLS-440-1	FASTENER						PENN ENGRG & MFG CORP. DOYLESTOWN, PA							8
																	7
		1		-15	FILLER WELD		.010	.062	4.5	AL ALY 718							6
		1		-13	FILLER WELD		.010	.20	11.2	AL ALY 718							5
		1		-12	BEAM (OPP)		.75	3.00	11.2	AL ALY 6061-T651 PL QQ-A-250/11					1		4
		1		-11	BEAM		.75	3.00	11.2	AL ALY 6061-T651 PL QQ-A-250/11					1		3
																	2
			PC145D1040 -1	BEAM ASSEMBLY											1		1
		-1		ASSEMBLIES													
QUANTITY REQD	CODE IDENT	PART NO. OR IDENTIFYING NO.	NOMENCLATURE OR DESCRIPTION	ZONE	QTY	THICK	WIDTH	LENGTH	MATERIAL / MATERIAL SPECIFICATION / CONDITION VENDOR NAME AND ADDRESS	PROCESS SPECIFICATION LINE NUMBERS	FINISH CODE	MARK CODE	FIELD NOTES	TRACE CODE	LINE NO.		
									LIST OF MATERIAL								

PC145D1040

PART NUMBER MARKING PER MIL-STD-130				LIST OF MATERIAL				UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSES PROPERTY OF FAIRCHILD HILLER CORPORATION			
								LAYOUT BY	JCH:WJS 4-12-72	FAIRCHILD HILLER FAIRCHILD REPUBLIC DIVISION FARMINGDALE, NEW YORK 11735	
								DRAWN BY		BEAM ASSEMBLY-	
								CHECKED			
								ENGINEER			
								STRUCTURES		SMS MICROTHRUSTER	
								APPROVED			
								CONTRACT NO. NAS-5-11494			
				WEIGHTS						SIZE CODE IDENT NO D 77751 PC145D1040	
				TOTAL WEIGHTS							
				DASH NO.							
				WEIGHT							
PC145D1005	SMS MICROTHRUSTER		1 OF 1	DO NOT SCALE DRAWING ALL DIMENSIONS ARE IN INCHES UNLESS OTHERWISE NOTED. TOLERANCES UNLESS NOTED XXX.01 XXXX.005 ANG2							
NEXT ASSEMBLY		USED ON	NEXT ASSY	FINAL ASSY							
APPLICATION			QUANTITY REQD						SCALE FULL		SHEET 1 OF

PC145D1040



FOLDOUT FRAME (2)







Figure 22. Electrical Interface Cover

[illegible]


C-27



**FOLDOUT**



C-26

[illegible]

0.29

FOLDOUT FRAME


[illegible]

Figure 24. Rear Faceplate Assembly

[illegible]



Figure 25. Shield

PC145D1052

- REQUIREMENTS FOR MACHINED PARTS  
(UNLESS OTHERWISE SPECIFIED):
- (A) MAX. RHR OF MACHINED SURFACES (EXCLUDING HOLES)  $\checkmark$  63 ALL OVER
  - (B) MAX. RHR OF HOLES  $\checkmark$
  - (C) ALL FILLETS  $\pm .040$  R  $\pm .010$
  - (D) ALL EDGES TO BE ROUNDED  $\pm .010$  MAX. (WHEN ROUNDING IS NOT SPECIFIED ON DWG.)
  - (E) TOLERANCES TO APPLY AFTER WELDING, HEAT TREATING, OR PLATING OPERATIONS. INITIAL DIMENSIONS OF SURFACES TO BE CADMIUM PLATED. SHALL NOT BE LESS THAN THE MINIMUM INDICATED FINISHED DIMENSIONS.
  - (F) APPLY PART NUMBER & INSPECTOR'S STAMP BY TAG.





Figure 26. Bridge

																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																					</
--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	----

PC145D1063

### REQUIREMENTS FOR MACHINED PARTS (UNLESS OTHERWISE SPECIFIED)

- (A) MAX. RHR OF MACHINED SURFACES (EXCLUDING HOLES)  $\checkmark$  ALL OVER
- (B) MAX. RHR OF HOLES  $\checkmark$
- (C) ALL FILLETS  $\frac{.090}{R} \pm .010$
- (D) ALL EDGES TO BE ROUNDED \_\_\_\_\_ MAX. (WHEN ROUNDED IS NOT SPECIFIED ON DWG.)
- (E) TOLERANCES TO APPLY AFTER WELDING, GRINDING OR PLATING OPERATIONS. INITIAL DIMENSIONS OF SURFACES TO BE CADMIUM PLATED, SHALL NOT BE LESS THAN THE MINIMUM INDICATED FINISHED DIMENSIONS.
- (F) APPLY PART NUMBER & INSPECTOR'S STAMP BY TAG.



1. SAND BLAST BOTH SIDES VERY GENTLY EXCEPT IN DESIGNATED MASKED AREAS

2 -11 BASE PLATE TO BE ATTACHED TO PTE-5904E TRANSFORMER DURING FABRICATION OF TRANSFORMER




Figure 27. Transformer Base

[illegible]

C-37, /

PC145D1064


FOLDOUT FRAME

FOLDOUT FRAME 2

FOLDOUT FRAME 3

COMPONENT IDENTIFICATION	
ITEM	PART NUMBER
C1	CYR30C103JM
C2	CKR06BX223KR
C3, C4	CKR06BX222KR
C5	CSR13E106KS
CR1	TXIN649
CR2	TX2N2326A
CR3	TXIN753A
CR4, CR5	TXIN414B
Q1, Q4, Q5, Q6	TX2N2222A
Q2	TX2N5251A
Q3	TX2N494B
R1, R2	RCR20G203JS
R3, R6	RCR20G103JS
R4, R5, R7, R8, R9, R10, R11, R12, R13, R14	RCR20G823JS
R15	RNR60E4993FS
R16	RCR20G152JS
R17	RCR20G102JS
R18	RCR20G510JS
R19	RCR20G822JS
R20	RCR20G105JS
R21	RCR20G512JS
R22	RCR20G104JS
A THRU H	FT-SM-2TURCZ
E1 THRU E6	A-2307EYELET (REF)

WIRING INFORMATION	
FROM	TO
E1	C
E2	B
E3	D
E4	G
E5	A
E6	H



NOTES

1. INSTALL TERMINALS FROM COMPONENT SIDE.

Figure 28. Delay Pulse Generator Board Assembly

COMPONENT IDENTIFICATION	
ITEM	PART NUMBER
C1	CYR30C103JM
C2	CKR06BX223KR
C3, C4	CKR06BX222KR
C5	CSR13E106KS
CR1	TXIN649
CR2	TX2N2326A
CR3	TXIN753A
CR4, CR5	TXIN414B
Q1, Q4, Q5, Q6	TX2N2222A
Q2	TX2N5251A
Q3	TX2N494B
R1, R2	RCR20G203JS
R3, R6	RCR20G103JS
R4, R5, R7, R8, R9, R10, R11, R12, R13, R14	RCR20G823JS
R15	RNR60E4993FS
R16	RCR20G152JS
R17	RCR20G102JS
R18	RCR20G510JS
R19	RCR20G822JS
R20	RCR20G105JS
R21	RCR20G512JS
R22	RCR20G104JS
A THRU H	FT-SM-2TURCZ
E1 THRU E6	A-2307EYELET (REF)

WIRING INFORMATION	
FROM	TO
E1	C
E2	B
E3	D
E4	G
E5	A
E6	H

QTY	SYM	UNIT	DESCRIPTION	DATE	BY
1			TX2N494B		
1			TX2N3251A		
1			TX2N2326A		
4			TX2N2222A		
2			TXIN414B		
1			TXIN753A		
1			TXIN649		
1			RNR60E4993FS		
1			RCR20G823JS		
1			RCR20G3822JS		
1			RCR20G122JS		
2			RCR20G510JS		
2			RCR20G203JS		
1			RCR20G152JS		
1			RCR20G102JS		
1			RCR20G404JS		
2			RCR20G105JS		
6			RCR20G822JS		
1			RCR20G102JS		
1			CYR30C103JM		
1			CSR13E106KS		
1			CKR06BX223KR		
2			CKR06BX222KR		
8			5771 FTSM-2TURCZ		
1			PC145D1074		
1			PC145D1074		
1			PC145D1074		

QTY	SYM	UNIT	DESCRIPTION	DATE	BY
1			FLUX		
1			SN63		
1			SOLDER		
1			TYPE 5 OR RMA		
1			QQ-S-571		
1			MIL-F-14256		
1			MIL-S-19500		
1			PC145D1071		
1			MIL-S-19500		
1			MIL-R-55182		
1			MIL-R-11		
1			MIL-C-23269		
1			MIL-C-39003		
1			MIL-C-39014		
1			MIL-C-39014		
1			(E.B. STIMPSON CO. BROOKLYN, N.Y.)		
1			PC145D1074		
1			PC145D1074		
1			PC145D1074		


QTY	SYM	UNIT	DESCRIPTION	DATE	BY
1			PC145D1065		
1			PC145D1065		
1			PC145D1065		

C-38

C-39

C-39.1

FOLDOUT FRAME 1



COMPONENT REFERENCE DESIGNATIONS ARE NOT SHOWN TO SCALE. APPLY COMPONENT REF DESIGNATIONS WITH .12 HIGH CHARACTERS USING CK13 BLACK (NR) INDICATES APPROX LOCATION OF H+ PLUS SYMBOL TO BE APPLIED

SECTION A-A  
TYP. EYELET ATTACHMENT  
SCALE: 4:1 APPROX.

PC145D1072

FOLDOUT FRAME 2

HOLE SYM	DRILL SIZE	INSTALL	QTY
A	#24 (.0550)	EYELET A-2307 (STIMPSON)	6
B	#27 (.1144)	DIA THRU	8
C	#33 (.1150)	DIA THRU	8
UNPKD	#61 (.0390)	DIA THRU	59
D	#74 (.0225)	DIA THRU	18

Figure 29. Delay Pulse Generator Drill Drawing


✓ 1172	CK-13	NR, BLACK	KRENGEL MFG-N.Y.C., N.Y.
6	577	A-2307	EYELET
1		-11 BOARD	2423-00-74 FL-GE062C1/OB11A MIL-P-3949
1		ASSEMBLY	PC145D 072-1 DELAY PULSE GENERATOR & FOLD FLOP BOARD ASSY.
1		ASSEMBLY	PC145D 072-1 DELAY PULSE GENERATOR & FOLD FLOP BOARD ASSY.

PC145D 072	1 OF 1	1 OF 1	DO NOT SCALE DRAWING ALL DIMENSIONS ARE IN INCHES UNLESS OTHERWISE NOTED TOLERANCES UNLESS NOTED EXT. DIM. TYP. UNLESS NOTED	FAIRCHILD EDARD ASSY- DELAY PULSE GENERATOR 77751 PC145D1072
------------	--------	--------	--	---



FOLDOUT FRAME

PRECEDING PAGE BLANK NOT FOR MATR



### DELAY PULSE GENERATOR

S/N 12

- REDUCE TO 4,000 ± .005

**NOTES-**  
1. THIS WORK IS PREPARED TO AN ENLARGED SCALE AND MUST BE REDUCED TO ACTUAL SIZE TO PRODUCE THE PRINTED WIRING BOARD.  
2. PRINTS OF THIS DWG ARE FOR REF ONLY.

**OLDOUT FRAME**

FOLDOUT FRAME 3

PC145D1073

PC145D107

Figure 30. Delay Pulse Generator Artwork

[illegible]

C-43, /

PC145D1073


REV	SM
	1
	3A

C-43

**FOLDOUT FRAME**

**FRAME**

FOLDOUT FRAME 3



① BOARD ASSY

- PC145D1076-1 BOARD ASSY

COMPONENT IDENTIFICATION	
ITEM	PART NUMBER
C1, C4	CKR06BX222KR
C2, C3	CKR06BX2224KR
CR1, CR2	TXIN414B
Q1, Q4	TX2N3251A
Q2, Q3	TX2N2222A
R1, R3, R8, R10	RCR20G102JS
R2, R6, R7, R9	RCR20G103JS
R11, R14	RCR20G510JS
R4, R5	RCR20G710JS
R12, R13	
E1 THRU E6	A-2307 EYELET (REF)

Figure 31. Pulse Driver Assembly

[illegible]

PC145D1075

C-44


C-44-1

C-45

Page intentionally left blank

FOLDOUT FRAME 2

**FOLDOUT** *Private* 3



REDUCE TO 4.000 ± .005

PC145D1077

PC45D1077

Figure 33. Pulse Driver Artwork

[illegible]

PCI45D1077

C-4<sup>o</sup>







C-50

C-49

FOLDOUT FRAME

FOLDOUT FRAME

2



ITEM	DESCRIPTION	STOCK SIZE	MATERIAL	REMARKS
1	CONE	.020 x 6.0 x 10.0	6061-0 AL ALY SH.	STRESS RELIEVE AFTER WELDING, HEAT TREAT TO T-6 CONDITION
2	EXTENSION	.020 x 1.5 x 2.8	6061-0 AL ALY SH.	
3	FLANGE	.090 x 3.2 x 3.5	6061-0 AL ALY SH.	
4	BASE	.062 x 2.5 x 3.0	NEMA G-10 FIBRE GLAS	
5	BASE EXTN	.032 x 2.5 x 3.0	NEMA G-10 FIBRE GLAS	



TOL: 3 PL ± .005 ANGULAR ± 0°15'

CONE ASY  
PC145D1080

Figure 34. Exhaust Cone Assembly

c-51

C-52



PC 145D1090  
CAPACITOR

Figure 35. Capaciter, SCD


FOLDOUT FRAME 1

FOLDOUT FRAME 2

PC145D1091

TYPE OF CHANGE	EAI INC	REWORK PERMIT YES NO	SYM

REVISIONS		DATE	APPROVED
DESCRIPTION			



-1 IGNITER PLUG

NOTES:  
1. APPLY A LIGHT BEAD OF EPOXY CEMENT (5% BY WT OF EPON 828 AND VERSAMID 140) ALL AROUND, THEN CURE AT 65°C (140°F) FOR 24 HOURS.

Figure 36. Igniter Plug, SCD

PC145D1091-1	IGNITER PLUG	(MAKE FROM 10-380729-1 BENDIX SCINTILLA DIV SYDNEY, N.Y.)	PC14556008											
QUANTITY REQD	SYM	VENDOR DATA PER	CODE IDENT	PART OR IDENTIFYING NO.	ZONE	NOMENCLATURE OR DESCRIPTION	DIA	THICK	WIDTH	LENGTH	MATERIAL	SPECIFICATION	TS 1000 PSI	UNIT WT
LIST OF MATERIAL														
PART NUMBER MARKING PER MIL-STD-130														
UNAUTHORIZED USE, MANUFACTURE OR REPRODUCTION IN WHOLE OR IN PART IS PROHIBITED. DRAWING, DESIGN AND OTHER DISCLOSURES PROPERTY OF FAIRCHILD HILLER CORPORATION.														
DIMENSIONS ARE IN INCHES UNLESS OTHERWISE NOTED														
DEC TOL SH MET. RAD GR ENGR														
2 PLACE ± BEND: STRUCT														
3 PLACE ±.005 COR: WEIGHTS														
ANGULAR ± DEBURR ALL EDGES														
APPLICABLE SPECIFICATIONS														
FINISH: PROJ ENGR														
HEAT TREAT: CONTRACT NO.														
BEND RELIEF: NAS-5-11494														
FOR ADDL SPEC SEE NOTE														
FAIRCHILD HILLER REPUBLIC AVIATION DIVISION FARMINGDALE, LONG ISLAND, NEW YORK														
IGNITER PLUG NEGATIVE ELECTRODE SMS MICROTHRUSTER														
SIZE CODE IDENT NO. C 77751 PC145D1091														
SCALE 2/1 UNLESS OTHERWISE NOTED SHEET														

C-55

C-56





APPENDIX D. TENTATIVE DRAWINGS OF WILMORE  
ELECTRONICS POWER CONDITIONER




Figure 38. Subassembly High Voltage Power Conditioner

PRECEDING PAGE BLANK NOT FILMED




Figure 39. Subassembly Delay Trigger Generator

Preceding page blank

PRECEDING PAGE BLANK NOT FILMED





Figure 40. Subassembly Auxiliary Power Supply

PRECEDING PAGE BLANK NOT FILLED

DATE	BY	REVISION RECORD	AUTH.	CHK.



- A. OUTPUT - TO INHIBIT OF DELAY GENERATOR
- B. -12.5v
- C. GND. FOR THREE COAX SHIELDS
- D. OUTPUT - TO RESET CONTROL OF H.V. CONVERTER. TWO SHIELDED WIRES
- E. INPUT FROM H.V. DIVIDER. ONE SHIELDED WIRE
- F. +12.5v
- G. HOLE FOR WIRES GOING TO POINTS A,B,C,D,E THREE COAX ; TWO STRANDED

TOLERANCES (EXCEPT AS NOTED)			
WILMORE ELECTRONICS CO., INC.			
DIMENSIONAL	3104	SCALE	DRAWN BY WFA
FRACTIONAL	1/16	APPROVED	12C0053
ANGULAR	DATE 1-20-72	DRAWING NUMBER	12C0053


REF: 11AFC/11, 16C0130.

11AFC/11, 16C0130.

11AFC/11, 16C0130.

Figure 41. Subassembly Comparator Regulator

Preceding page blank



A: TO 2T<sub>2</sub> - N<sub>2</sub>  
 B: TO 2T<sub>2</sub> - N<sub>2</sub>  
 C: FROM 2R<sub>13</sub> + ANODE 2D<sub>1</sub>  
 D: COMMON GND NODE  
 E: COMMON ENABLE POINT  
 F: FILTERED +29.4v POINT  
 G: TO 5L<sub>1</sub>  
 H: TO 5L<sub>1</sub>  
 I: +29.4v POWER INPUT EMI FILTER  
 J: TO HARD WIRE MONITOR (J<sub>2</sub> - 5)  
 K: +1450v TO 2R<sub>14</sub> + 2R<sub>18</sub>

2D10 AND 2R14 SHOWN ON 16C0129 SCHEMATIC  
 SD, SC<sub>1</sub>, SC<sub>2</sub> ARE SHOWN ON 16C0131 SCHEMATIC

REF 11A0D72 16C0131 12C0056

TOLERANCES (UNLESS OTHERWISE SPECIFIED)				WILMORE ELECTRONICS CO., INC.			
DECIMAL	2	3	4	SCALE	DRAWN BY	APPROVED BY	
FRACTIONAL	2	3	4	TITLE	SUBASSEMBLY POWER TRANSFORMER		
ANGULAR	2	3	4	DATE	2-7-72	DRAWING NUMBER	12C0056

Figure 42. Subassembly Power Transformer




Figure 43. Drill Drawing for 15C0181





Figure 44. Drill Drawing for 15C0182

PRECEDING PAGE BLANK NOT FILLED

[illegible]

- UNMARKED HOLES : "74 DRILL  
HOLES A : "72 DRILL  
HOLES B : "70 DRILL  
HOLES C : "65 DRILL  
HOLES D : "55 DRILL  
HOLES E : "50 DRILL  
HOLES F : 9/16 DRILL  
HOLES G : "44 DRILL  
HOLES H : 3/32 DRILL

TOLERANCES (EXCEPT AS NOTED)			
ORIGINAL	Revised on 1/1/74 1/1/74 ME	SCALE	DRAWN BY LFA
2			APPROVED BY [Signature]
FRAGMENTAL		TITLE	
2		DALLAS FOR 15C0195	
ANNUAL	DATE	DRAWING NUMBER	
2	1/1/74	15C0192	


REF. NUMBER 160111, 1200153, --

**Figure 45. Drill Drawing for 15C0185**



PRECEDING PAGE BLANK NOT FILLED

DATE	BY	REVISION	RECORD	AUTH.	OR.	CK.



- UNMARKED HOLES : # 74 DRILL
- HOLES A : # 72 DRILL
- HOLES B : # 70 DRILL
- HOLES C : # 65 DRILL
- HOLES D : # 55 DRILL
- HOLES E : # 50 DRILL
- HOLES F : # 44 DRILL
- HOLES G : # 44 DRILL
- HOLES H : # 32 DRILL

TRIM ALL SURROUNDING FRAME

REF: 11AC170, 14CC129, 12.CC051.

TOLERANCES (UNLESS OTHERWISE SPECIFIED)				WILMORE ELECTRONICS CO., INC.			
ORIGINAL	DATE	SCALE	DRAWN BY	APPROVED BY			
1	10-19-72		WFA	HFB			
FRACTIONAL	TITLE			DRAWING NUMBER			
2	DRILLING DWG FOR 15C0188			15C0193			
ANGULAR	DATE	DRAWING NUMBER					
3	11-1-72	15C0193					

WILMORE ELECTRONICS CO., INC.

WILMORE ELECTRONICS CO., INC.

Figure 46. Drill Drawing for 15C0188

Preceding page blank

PRECEDING PAGE BLANK NOT FOR ATTN





Figure 47. Drill Drawing for 15C0189

Preceding page blank



12C0051

PRECEDING PAGE BLANK NOT FILLED




Figure 49. Schematic for Subassembly 12C0052

Preceding page blank





Figure 50. Schematic for Subassembly  
 12C0050

Preceding page blank

PRECEDING PAGE BLANK NOT FILMED



TOLERANCES (EXCEPT AS NOTED)			
WILMORE ELECTRONICS CO., INC.	DATE	SCALE	DRAWN BY
3/24	1-26-72		WFA
APPROVED BY			
1/6			
FRACTIONAL	TITLE	FOR 12C0053 SUBASSY	
±	SCHEMATIC		
ANGULAR	DATE	DRAWING NUMBER	
±	1-26-72	16C0130	

PRECEDING PAGE BLANK NOT FILLED




Figure 52. Converter Schematic

Preceding page blank

PRECEDING PAGE BLANK NOT FILMED




Figure 53. Enclosure

Preceding page blank



PRECEDING PAGE BLANK NOT FILMED




Figure 54. Cover

Preceding page blank